



85656279



**IP20**

## KNX radio wall-transmitter 2gang flat quicklink, K.1, p. white glossy

### Technical properties

#### Functions

ETS additional functions	ETS additional functions: +6 scenes, operating mode on/off, push-button, status display, dimming value
Function	reset function (to factory setting) ; easy additional functions: +6 scenes, on/off operating mode, 1 up/down button control
Quicklink functions	quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory

#### Controls and indicators

Operation	operating areas configurable as one or two-area operation
Button / push-button	with configuration button

#### Connectivity

Radio protocol	KNX Radio
Receiver category	2

#### Dimensions

Assembling height	14 mm
-------------------	-------

#### Frequency

Radio transmission frequency	868.3 MHz
------------------------------	-----------

#### Power

Radio transmission power	< 10 mW
--------------------------	---------

#### Battery

Battery service life [years]	≈ 5
Battery / storage battery	with lithium coin cell battery 3 V type: CR 2430

#### Materials

Colour of design line	polar white
RAL colour	RAL 9010 - Pure white
Surface appearance	glossy

#### LED control

LED	with configuration LED ; with transmission status and battery status LED, red/green/orange
-----	--

#### Installation, mounting

Installation mode	for flat surface mounting and extension of combinations
-------------------	---

**Connection**

Bus connection	integration in the KNX radio/TP gateway, surface-- mounted, into the KNX TP system
----------------	---

**Settings**

Programming	toolless quicklink configuration using buttons and LED display ; top and bottom operating areas are freely configurable
-------------	---

**Equipment**

Number of radio channels	4
Number of quicklink links	max. 20 transmitter/receiver
Transmitter duty cycle	1 %

**Safety**

REACH conform	No
RoHS conform	Yes
Halogen free	No
Protection	with dismantling protection

**Use conditions**

Operating temperature	-5...45 °C
Energy-saving	low intrinsic energy requirement
Relative humidity (without condensation)	0...65 % (without condensation)

**Identification**

Application, usage	KNX radio- operating systems
Main design line	Berker K.1
Secondary design line(s)	Berker.Net ; Berker K.1