



75663590



## B.IQ push-button 3gang thermostat, display, KNX - B.IQ, glass p. white

### Technical properties

#### Functions

With room temperature controller	Yes
Function	with valve protection function
Timers	with room temperature timer and 2-week timer functions

#### Compatibility

Extension unit	extension unit for light scene push-button
----------------	--

#### Controls and indicators

With LED indication	Yes
Number of buttons	3
Operation	one push-button operation for switching, pushing, shutters and dimming

#### Dimensions

Width of rail mounted device (RMD)	0 modules
Height	119.6 mm
Width	88.5 mm

#### Measurement

Value transmitter	value transmitter for dimming, position, brightness and temperature values 1 and 2 byte
-------------------	---

#### Materials

Colour of design line	glass polar white
RAL colour	RAL 9010 - Pure white
Material	glass
Material family	Glass

#### LED control

LED	with blue operation LED and 6 white status LEDs (labelling field illumination)
-----	--

#### Settings

Parameterisation	single and two push-button operation parameterisable
------------------	--

#### Accessories included

Box	for installation in single standard wall boxes
Matching products	for additional products to complement the installation in matching colours/materials, refer to the Design platform S.1/B.x, for glass frames in the same "style" for additional applications, see the Design line B.7

**Equipment**

---

Product type:	product type: B.IQ
Control	for individual single room temperature control

---

**Software**

---

Update	with flash-controller technology
--------	----------------------------------

---

**Safety**

---

Protection	with dismantling protection
------------	-----------------------------

---

**Use conditions**

---

Operating temperature	-5...45 °C
Energy efficiency class	IV (2%)

---

**Identification**

---

Application, usage	KNX - operating systems
Product family	product family: push-button
Release issue	2.6
Main design line	KNX - Berker B.IQ
Secondary design line(s)	KNX, Berker B.IQ

---