



80960282

IP20



**Cover for 1gang for push-button module, clearlens, S.1/B.3/B.7, white glossy**

**Technical properties**

**Functions**

|                     |   |
|---------------------|---|
|                     | operating concept "independent push-button" function predefined ; operating concept for "roller shutter/blind" function predefined ; switching of scenes (1..8) possible ; brightness value of the status LED for day/nighttime operation preset, change-over for day/nighttime operation possible ; integrated temperature sensor with output of the measured values ; Colour of status LED uniformly adjustable for complete device ; push-button functions: including switching, dimming, roller shutter/blind, timer, priority, operating mode changeover |
| Easy link functions |   |

|          |   |
|----------|---|
| Function | Function for manual interruption of automatic functions already triggered |
|----------|---|

|          |   |
|----------|---|
| Function | operating surfaces as buttons (single-surface operation) and rockers (two-surface operation) ; the brightness of status LEDs are individually adjustable for button/ rocker function ; brightness value of the status LEDs for day/nighttime operation adjustable via object or manually ; value transmitter for dimming, position, brightness temperature values 1 and 2 byte ; integrated temperature sensor with output of the measured values via object ; parameter defineable lock function ; button/rocker functions for switching, dimming, roller shutter/blind, value transmitter 1/2 byte, room thermostat extension unit, priority, scene, automatic control deactivation |
|----------|---|

**Controls and indicators**

|                      |   |
|----------------------|---|
| Operation            | operating areas configurable as one or two-area operation |
| Button / push-button | with programming button and red programming LED           |

**Voltage**

|                            |              |
|----------------------------|--------------|
| Operating voltage over bus | 21...32 V DC |
|----------------------------|--------------|

**Dimensions**

|        |       |
|--------|-------|
| Height | 55 mm |
|--------|-------|

**Power**

|                        |          |
|------------------------|----------|
| Power consumption, KNX | ≈ 108 mW |
|------------------------|----------|

**Camera**

|      |  |
|------|--|
| Lens | with clear lens for RGB status display of the push-button module |
|------|--|

**Materials**

|                           |           |
|---------------------------|-----------|
| Colour of design line     | white     |
| Surface appearance        | glossy    |
| Type of surface treatment | untreated |

**Connection**

|                   |  |
|-------------------|--|
| Bus coupling unit | with integral bus coupling unit        |
| Bus connection    | bus connection via connecting terminal |

**Settings**

|                               |              |
|-------------------------------|--------------|
| Supported configuration modes | system, easy |
|-------------------------------|--------------|

**Equipment**

|              |  |
|--------------|--|
| Buzzer/siren | with integrated buzzer for acoustic identification of the device within the system |
|--------------|--|

**Use**

|  |                 |
|--|-----------------|
| Differentiation characteristic 2 - Sales | with clear lens |
|--|-----------------|

**Safety**

|               |                             |
|---------------|-----------------------------|
| REACH conform | Yes                         |
| RoHS conform  | Yes                         |
| Halogen free  | No                          |
| Protection    | with dismantling protection |

**Use conditions**

|                               |   |
|-------------------------------|---|
| Operating temperature         | -5...45 °C  |
| Storage/transport temperature | -20...70 °C (storage at > 45°C reduces the service life)                    |
| Temperature                   | integrated temperature sensor with output of the measured values via object |

**Identification**

|                          |  |
|--------------------------|--|
| Application, usage       | KNX - operating systems                    |
| Product family           | product family: push-button                |
| Main design line         | KNX - Berker S.1/B.3/B.7                   |
| Secondary design line(s) | KNX ; Berker S.1 ; Berker B.3 ; Berker B.7 |