

85341273

## IR motion detector comfort 1.1 m, K.5, stainless steel matt, lacquered

## **Technical properties**

Mode of operation	$\mu$ -processor controlled mode of operation
	Teach function for response brightness via button with keylock ; Party function for switching on for 2 hours ; with memory function for presence simula
Function	tion
Operating mode	step operation with immunity time (e.g. for stai light/impact current circuits
Controls and indicators	
Button / push-button	with button for on/off/automati
Dimensions	
Assembling height	34 mr
Nominal mounting height	1.1 n
Tripping	
immunity time	≈ 10
Measurement	
Detection field, rectangular shaped	≈ 12 x 16 n
Reach distance	
Range, frontal	≈ 12 n
Range, side	each ≈ 8 n
Detection	
Number of detection levels	
Detection angle, settable	each side ≈ 4590
Detection field Ø, on floor	0 r
Materials	
<b>Materials</b> Colour of design line	stainless stee
Colour of design line	
Colour of design line Material / workmanship	stainless stee lacquere ≈ 51000 lx , daytime operatio
Colour of design line Material / workmanship Lighting control	lacquere
Colour of design line Material / workmanship <b>Lighting control</b> Response brightness, adjustable	lacquere

Response value luminosity adjustable

Response value sensitivity adjustable	Yes
Response sensitivity, settable	10100 %
Short time mode	200 ms
Delay time	≈ 180 s
Delay time, adjustable	≈ 10 s30 mr
Switch-off pre-warning to dimming value 50% for	30 :
Safety	
REACH conform	No
RoHS conform	Ye
Halogen free	N
Protection	with dismantling protection
Use conditions	
Operating temperature	-545 °C
Energy-saving	low intrinsic energy requiremen
Relative humidity (without condensation)	065 % (without condensation)
Identification	
Application, usage	Light control ; Motion detecto
Main design line	Berker K.S
Secondary design line(s)	Motion detector ; Berker K.
Instructions	
	Continuous direct sunlight penetrating the upward- pointing detection plane can result in failure of the

Information text

Continuous direct sunlight penetrating the upward-pointing detection plane can result in failure of the motion detector. Only suitable for indoor areas!