

Berker S.1/B.3/B.7

Berker S.1, Berker B.3, Berker B.7



3315408989

VGA soc. out., S.1/B.3/B.7, p. white glossy

Technical properties

| nne | | - 1 Acc - |
|---------|------|-----------|
| nne | CTIV | VITV |
| | | |

| Connectivity | |
|------------------------------------|--|
| Outlet | with straight outlet |
| Plug type | S-VGA compatible |
| Connectors / jacks | with 15pole D-subminiature jack (front) |
| Dimensions | |
| Insertion depth | 12 mm |
| Frequency | |
| Frequency range video | max. 160 MHz |
| Screen | |
| Resolution | max. 1280 x 1024 px |
| Materials | |
| Colour of design line | polar white |
| Colour | polarwhite |
| RAL colour | RAL 9010 - Pure white |
| Material | Plastic/metal |
| Installation, mounting | |
| Installation mode | without spreader claws, for screw fastening |
| Connection | |
| Type of connection | with backside jack for connecting to pre-assembled VGA cable |
| Connection | with 15pole D-subminiature double jack |
| Equipment | |
| Supporting plate / Supporting ring | with supporting ring |
| Safety | |
| REACH conform | Yes |
| RoHS conform | Yes |
| Identification | |
| Application, usage | Communication technology |

Instructions

Main design line

Secondary design line(s)

For connecting PCs, notebooks, etc. to display devices such as monitors (including LCD monitors) and projectors.; Observe the instructions of the cable and device manufacturers for maximum VGA cable lengths!; Fränkische: "Multimedia tube" for laying pre-assembled connection cable, Art. no. 294.10.092; Installation recommendation: Kaiser: "Electronic box" for compliance with the permissible bending radii, Art. No. 1068-02 or 9062-74

Information text