




80960285

IP20



## Cover for 1gang for push-button module, clearlens, S.1/B.3/B.7, ant., matt

### Technical properties

#### Architecture

|             |                |
|-------------|----------------|
| Fixing mode | flush-mounting |
|-------------|----------------|

#### Functions

|                     |   |
|---------------------|---|
| Easy link functions | operating concept "independent push-button" function predefined ; operating concept for "roller shutter/blind" function predefined ; switching of scenes (1..8) possible ; brightness value of the status LED for day/nighttime operation preset, change-over for day/nighttime operation possible ; integrated temperature sensor with output of the measured values ; Colour of status LED uniformly adjustable for complete device ; push-button functions: including switching, dimming, roller shutter/blind, timer, priority, operating mode changeover |
|---------------------|---|

|          |   |
|----------|---|
| Function | Function for manual interruption of automatic functions already triggered |
|----------|---|

|          |   |
|----------|---|
| Function | operating surfaces as buttons (single-surface operation) and rockers (two-surface operation) ; the brightness of status LEDs are individually adjustable for button/ rocker function ; brightness value of the status LEDs for day/nighttime operation adjustable via object or manually ; value transmitter for dimming, position, brightness temperature values 1 and 2 byte ; integrated temperature sensor with output of the measured values via object ; parameter defineable lock function ; button/rocker functions for switching, dimming, roller shutter/blind, value transmitter 1/2 byte, room thermostat extension unit, priority, scene, automatic control deactivation |
|----------|---|

### Controls and indicators

|                      |   |
|----------------------|---|
| Operation            | operating areas configurable as one or two-area operation |
| Button / push-button | with programming button and red programming LED           |

### Voltage

|                            |              |
|----------------------------|--------------|
| Operating voltage over bus | 21...32 V DC |
|----------------------------|--------------|

### Dimensions

|        |       |
|--------|-------|
| Height | 55 mm |
|--------|-------|

### Power

|                        |          |
|------------------------|----------|
| Power consumption, KNX | ≈ 108 mW |
|------------------------|----------|

### Camera

|      |  |
|------|--|
| Lens | with clear lens for RGB status display of the push-button module |
|------|--|

### Materials

|  |  |
|--|--|
| Colour of design line                    | anthracite   |
| RAL colour                               | RAL 7021 - Black grey  |
| Material                                 | thermoplastic  |
| Surface appearance                       | matt   |
| Type of surface treatment                | untreated  |
| <b>Connection</b>                        |  |
| Bus coupling unit                        | with integral bus coupling unit  |
| Bus connection                           | bus connection via connecting terminal   |
| <b>Settings</b>                          |  |
| Supported configuration modes            | system, easy   |
| <b>Equipment</b>                         |  |
| Buzzer/siren                             | with integrated buzzer for acoustic identification of the device within the system |
| <b>Use</b>                               |  |
| Differentiation characteristic 2 - Sales | with clear lens  |
| <b>Safety</b>                            |  |
| Protection index IP                      | IP20   |
| Protection                               | with dismantling protection  |
| <b>Use conditions</b>                    |  |
| Operating temperature                    | -5...45 °C   |
| Storage/transport temperature            | -20...70 °C (storage at > 45°C reduces the service life)                           |
| Temperature                              | integrated temperature sensor with output of the measured values via object        |
| <b>Identification</b>                    |  |
| Application, usage                       | KNX - operating systems  |
| Product family                           | product family: push-button  |
| Main design line                         | KNX - Berker S.1/B.3/B.7   |
| Secondary design line(s)                 | KNX ; Berker S.1 ; Berker B.3 ; Berker B.7   |