



80960371

IP20



Cover for 2gang for push-button module, clearlenses, K.5, al., matt, lacq.

### Technical properties

#### Architecture

Fixing mode flush-mounting

#### Functions

operating concept "independent push-button" function predefined ; operating concept for "roller shutter/blind" function predefined ; switching of scenes (1..8) possible ; brightness value of the status LED for day/nighttime operation preset, change-over for day/nighttime operation possible ; integrated temperature sensor with output of the measured values ; Colour of status LED uniformly adjustable for complete device ; push-button functions: including switching, dimming, roller shutter/blind, timer, priority, operating mode changeover

Easy link functions

#### Controls and indicators

Button / push-button with programming button and red programming LED

#### Voltage

Operating voltage over bus 21...32 V DC

#### Dimensions

Height 55 mm

#### Power

Power consumption, KNX  $\approx$  108 mW

#### Camera

Lens with 2 clear lenses for the RGB status display of the push-button module

#### Materials

RAL colour RAL 9006 - White aluminium

Material thermoplastic

Surface appearance matt

Type of surface treatment Painted

#### Connection

Bus coupling unit with integral bus coupling unit

Bus connection bus connection via connecting terminal

#### Settings

Supported configuration modes system

#### Use

**Safety**

---

Protection index IP	IP20
---------------------	------

---

Protection	with dismantling protection
------------	-----------------------------

**Use conditions**

---

Operating temperature	-5...45 °C
-----------------------	------------

---

Storage/transport temperature	-20...70 °C (storage at > 45°C reduces the service life)
-------------------------------	--

**Identification**

---

Application, usage	KNX - operating systems
--------------------	-------------------------

---

Product family	product family: push-button
----------------	-----------------------------

---

Main design line	KNX - Berker K.1/K.5
------------------	----------------------

---

Secondary design line(s)	KNX, Berker K.1, Berker K.5
--------------------------	-----------------------------