


85145131



IP20

KNX radio button 1gang quicklink, R.1/R.3/1930/R.cl., black glossy

Technical properties

Functions

| | |
|--------------------------|--|
| | ETS additional functions: +6 scenes, 1 button control up/down, operating mode on/off, dimming value, brightness display, push-button, status display, forced control |
| ETS additional functions | |

Quicklink functions

quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory

Connectivity

| | |
|-------------------|-----------|
| Radio protocol | KNX Radio |
| Receiver category | 2 |

Dimensions

| | |
|----------|---------|
| Diameter | 57.4 mm |
|----------|---------|

Power

| | |
|--------------------------|---------|
| Radio transmission power | < 10 mW |
|--------------------------|---------|

Materials

| | |
|-----------------------|----------------------|
| Colour of labelling | 217,217,217 |
| Colour of design line | black |
| RAL colour | RAL 9005 - Jet black |
| Material | thermoplastic |
| Material for printing | PC-PMA black |

Equipment

| | |
|---------------------------|------------------------------|
| Number of radio channels | 2 |
| Number of quicklink links | max. 20 transmitter/receiver |
| Type of configuration | Laserdruck |
| Transmitter duty cycle | 1 % |

Safety

| | |
|------------|-----------------------------|
| Protection | with dismantling protection |
|------------|-----------------------------|

Use conditions

| | |
|--|---------------------------------|
| Operating temperature | -5...45 °C |
| Relative humidity (without condensation) | 0...65 % (without condensation) |

Identification

| | |
|--------------------------|--|
| Application, usage | Light control, KNX radio- operating systems |
| Main design line | Berker R.1/R.3/R.8/Serie 1930/R.classic |
| Secondary design line(s) | Berker R.1, Berker R.3, Serie 1930, Series R.classic |

Instructions

Note: When integrating this product into the Serie 1930, the 1gang frame for centre plate Ø 58 mm, order no.: 1382 0... may only be used. Installation in multiple combinations of the Serie 1930 is not possible!

Special note text