



85745289



**KNX radio timer quicklink, display, S.1/B.3/B.7, p. white glossy**

**Technical properties**

**Functions**

Astronomic time shift	± 2 h
Random number generator	± 15 mn
ETS additional functions	ETS additional functions: +6 scenes, operating mode on/off, scene loading, time dimming value, push-button, status display
Function	with keylock
Quicklink functions	quicklink functions: switching, 2 scenes, time switching, NO contact push-button, forced control
Slide switch	with switchover manual/automatic mode
Power reserve	≈ 8 h

**Connectivity**

Radio protocol	KNX Radio
----------------	-----------

**Dimensions**

Width of rail mounted device (RMD)	0 modules
------------------------------------	-----------

**Power**

Radio transmission power	< 10 mW
--------------------------	---------

**Measurement**

Running accuracy	± 3 min/year
------------------	--------------

**Battery**

Power reserve [years]	0 a
-----------------------	-----

**Materials**

Colour of design line	polar white
Material	thermoplastic

**Settings**

Time	with automatic summer-/winter time switching (can be switched off)
------	--

**Equipment**

Number of radio channels	1
Number of quicklink links	max. 20 transmitter/receiver
Number of switching times for on/off	20

**Use**

Differentiation characteristic 2 - Sales	with display
--	--------------

**Safety**

---

Protection index IP	IP20
---------------------	------

---

Protection	with dismantling protection
------------	-----------------------------

**Use conditions**

---

Operating temperature	-5...45 °C
-----------------------	------------

---

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

**Identification**

---

Application, usage	Light control, KNX radio- operating systems
--------------------	---

---

Main design line	Berker S.1/B.3/B.7
------------------	--------------------

---

Secondary design line(s)	Berker S.1, Berker B.3, Berker B.7
--------------------------	------------------------------------