



EE807

## IP30

### Remote control for settings for presence detectors 360° monobloc

#### Technical properties

##### Architecture

Number of keys 18

##### Configuration

Module télécommande

##### Compatibility

Sensors associated EE815, EE816, TCC5xxx

##### Controls and indicators

Operation 3 configuration ranges for control, switch-off delay, brightness threshold

Button / push-button 15 push-buttons with integrated status-LED

##### Dimensions

Dimensions (LLxwwxhh) 70x10x120

##### Reach distance

Max. transmission range 3 m

##### Battery

Battery service life [years] ≈ 2.5

Number and type of replacement batteries 1x 3V CR2032

##### Detection

IR RC6 code

##### LED control

LED additional acknowledgement LED for displaying the IR transmission

##### Settings

Setting setting of the brightness threshold manually, by default values or teach-in mode ; default settings can be selected for the brightness threshold daylight, office, corridor

##### Accessories included

Accessory type Manual transmitter for movement sensor

##### Equipment

Cylinder 2 configuration memories for identical configuration of several presence detectors

##### Safety

REACH conform	No
RoHS conform	Yes
Halogen free	No

---

**Instructions**

Special application information                      also for KNX applications - KNX IR presence detector