## Product data sheet HHA041U





HHA041U

## Moulded Case Circuit Breaker x160 4P 25kA 40A

## **Technical properties**

Number of poles	4 F
Functions	
Complete device with protection unit	Yes
Trip Unit	TM A/F
Integrated earth fault protection	Να
Configuration	
Number of modules	(
Main electrical features	
Rated operational voltage Ue	220 / 415 \
Frequency	50/60 H
Voltage	
Rated insulation voltage	690 \
Rated impulse withstand voltage	8 k <sup>v</sup>
With under voltage release	N
Electric current	
Rated current	40 /
Rated ultimate short-circuit breaking capacity Icu under 690V AC IEC 60947-2	4 k/
Thermal protection nob setting xIN	0.63 / 0.8 / 2
Thermal setting current on neutral pole	1
Breaking capacity on 1 pole for IT 230V NF 60947-2	15 k/
Breaking capacity on 1 pole for IT 400V NF 60947-2	9 k/
Rated service breaking capacity Ics AC according IEC 60947-2	100 %
Rated ultimate short-circuit breaking capacity Icu under 230V AC IEC 60947-2	35 k.
Rated ultimate short-circuit breaking capacity Icu under 240V AC IEC 60947-2	25 k
Rated ultimate short-circuit breaking capacity Icu under 400V AC IEC 60947-2	25 k
	23 N
Rated ultimate short-circuit breaking capacity Icu under 415V AC IEC 60947-2	25 k/

## **Current correction factors**

Subject to technical modifications

Correction factor of rating current for 2 devices placed side-by-side	1
Correction factor of rating current for 3 devices placed side-by-side	1
Correction factor of rating current for 4 and 5 devices placed side-by-side	1
Correction factor of rating current for 6 devices placed side-by-side	1
Power	
Total power loss under IN	11 W
Power loss per pole at In	3.7 W
Tripping	
Tripmode	TM
Thermal protection trip time	0 ms
Time of response when opening	10 ms
Electrical specifications	
Magnetic trip delay time	0 ms
Endurance	
Electric endurance in number of cycles	1000
Number of mechanical operations	4000
Installation, mounting	
DIN rail mounting with optional adaptator	Yes
Commention	
LONDECTION	
Connection Connection cross-sect. rigid cable	4 / 95mm²
Connection cross-sect. rigid cable	4 / 95mm²
Connection cross-sect. rigid cable	
Connection cross-sect. rigid cable	A 000
Connection cross-sect. rigid cable Settings Range of the magnetic adjustment Setting type In or Ith	600 A
Connection cross-sect. rigid cable Settings Range of the magnetic adjustment Setting type In or Ith Equipment	600 A
Connection cross-sect. rigid cable Settings Range of the magnetic adjustment Setting type In or Ith	600 A IN
Connection cross-sect. rigid cable Settings Range of the magnetic adjustment Setting type In or Ith Equipment Number of auxiliary contacts as normally	600 A IN (
Connection cross-sect. rigid cable Settings Range of the magnetic adjustment Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-	A 000 IN C
Connection cross-sect. rigid cable Settings Range of the magnetic adjustment Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact	A 000 IN C
Connection cross-sect. rigid cable Settings Range of the magnetic adjustment Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change- over contact Motor drive optional	A 000 IN C
Connection cross-sect. rigid cable Settings Range of the magnetic adjustment Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change- over contact	600 A IN C C C No
Connection cross-sect. rigid cable Settings Range of the magnetic adjustment Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change- over contact Motor drive optional Use cases Category of use	600 A IN C C C No
Connection cross-sect. rigid cable Settings Range of the magnetic adjustment Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change- over contact Motor drive optional Use cases	600 A IN C C C C C C C C C C C C C C C C C C
Connection cross-sect. rigid cable Settings Range of the magnetic adjustment Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change- over contact Motor drive optional Use cases Category of use Standards	600 A IN C C C C C C C C C C C C C C C C C C
Connection cross-sect. rigid cable Settings Range of the magnetic adjustment Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change- over contact Motor drive optional Use cases Category of use Standards Standard text	4 / 95mm <sup>2</sup> 600 A IN 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0 0
Connection cross-sect. rigid cable Settings Range of the magnetic adjustment Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change- over contact Motor drive optional Use cases Category of use Standards Standard text European directive WEEE	600 A IN C C C C C C C C C C C C C C C C C C