

45 kA



HNE970H

Moulded Case Circuit Breaker h1000 3P 50kA 1000A LSI

Technical properties

3 P
Yes
LSI
No
12
220 / 690 V
50/60 Hz
800 V
8 kV
No
1000 A
20 kA
0.4 / 0.5 / 0.63 / 0.8 / 0.9 / 0.95 / 1
45 kA
9 kA
100 %
85 kA
75 kA
75 kA 50 kA

Current correction factors

Rated ultimate short-circuit breaking capacity Icu under 440V AC IEC 60947-2

Correction factor of rating current for 2 devices placed side-by-side	1
Correction factor of rating current for 3 devices placed side-by-side	:
Correction factor of rating current for 4 and 5 devices placed side-by-side	
Correction factor of rating current for 6 devices placed side-by-side	
Power	
Total power loss under IN	186 V
Power loss per pole at In	62 N
Tripping	
Tripmode	L
Thermal protection trip time	5 / 10 / 11 / 16 / 21 m
Time of response when opening	10 m
Electrical specifications	
Magnetic trip delay time	100 to 200 m
Endurance	
Electric endurance in number of cycles	100
Number of mechanical operations	400
Installation, mounting	
Installation, mounting DIN rail mounting with optional adaptator	N
DIN rail mounting with optional adaptator	N
DIN rail mounting with optional adaptator Connection	
DIN rail mounting with optional adaptator	
DIN rail mounting with optional adaptator Connection	
DIN rail mounting with optional adaptator Connection Type of connection	Termin
Connection Type of connection Settings	Termin 5600 / 7000 / 8820 / 10000 / 10000 / 10000 / 10000
Connection Type of connection Settings Range of the magnetic adjustment	Termin 5600 / 7000 / 8820 / 10000 / 10000 / 10000 / 10000 / 2.5 / 5 /
Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN	Termin 5600 / 7000 / 8820 / 10000 / 10000 / 10000 / 10000 / 2.5 / 5 /
Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith	Termin 5600 / 7000 / 8820 / 10000 / 10000 / 10000 / 10000 / 2.5 / 5 /
Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally	Termin 5600 / 7000 / 8820 / 10000 / 10000 / 10000 / 10000 / 2.5 / 5 /
Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally	Termin 5600 / 7000 / 8820 / 10000 / 10000 / 10000 / 10000 / 2.5 / 5 /
Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-	Termin 5600 / 7000 / 8820 / 10000 / 10000 / 10000 / 1000 2.5 / 5 / IrT
Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact	Termin 5600 / 7000 / 8820 / 10000 / 10000 / 10000 / 1000 2.5 / 5 / IrT
Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional	Termin 5600 / 7000 / 8820 / 10000 / 10000 / 10000 / 1000 2.5 / 5 / IrT
Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional Use cases	Termin. 5600 / 7000 / 8820 / 10000 / 10000 / 10000 2.5 / 5 / IrT
Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional Use cases Category of use	Termina 5600 / 7000 / 8820 / 10000 / 10000 / 10000 / 1000 2.5 / 5 / IrT Ye

Operating temperature	-2570 °C
Altitude	2000 m
Storage/transport temperature	-3570 °C