



## MT320A

## MCB 3P 6kA B-20A 3M

## **Technical properties**

- A		le i		ct		-
$\mathbf{A}$	rc.	ш	пе	CL	ш	re

Number of protected poles	3
Number of poles	3 P
Type of pole	3 P
Curve	В
Functions	
Concurrently switching N-neutral	No
Configuration	
Number of modules	3
Connectivity	
Top connection alignement for modular devices	Aligned terminal
Bottom connection alignement for modular devices	Aligned terminal
Main electrical features	
Rated short circuit breaking capacity Icn AC according IEC60898-1	6 kA
Rated operational voltage Ue	230 / 400 V
Frequency	50/60 Hz
Voltage	
Rated insulation voltage	500 V
Rated impulse withstand voltage	4000 V
Electric current	
Rated current	20 A
Rated service breaking capacity Ics AC according IEC 60898-1	6 kA
min/maxi threshold value of the AC thermal operation	1.13 / 1.45 ln
Magnetic regulating currrent	3 / 5 In
min/maxi threshold value of the DC magnetic operation	4 / 7 In
min/maxi threshold value of the DC thermal operation	1.13 / 1.45 ln
Breaking capacity on 1 pole for IT 400V NF	3 kA
Rated short circuit breaking capacity Icn	
under 400V AC according IEC60898-1	6 kA

Electric current / temperature	
Rating current -25°C	24.6 A
Rating current -20°C	24.3 A
Rating current -15°C	23.9 A
Rating current -10°C	23.5 A
Rating current -5°C	23.1 A
Rating current 0°C	22.7 A
Rating current 5°C	22.2 A
Rating current 10°C	21.8 A
Rating current 15°C	21.4 A
Rating current 20°C	20.9 A
Rating current 25°C	20.5 A
Rating current 30°C	20 A
Rating current 35°C	19.5 A
Rating current 40°C	19 A
Rating current 45°C	18.5 A
Rating current 50°C	18 A
Rating current 55°C	17.5 A
Rating current 60°C	16.9 A
Rating current 65°C	16.4 A
Rating current 70°C	15.9 A
Current correction factors	
Correction factor of rating current for 2 devices placed side-by-side	1
	0.95
devices placed side-by-side  Correction factor of rating current for 3	
devices placed side-by-side  Correction factor of rating current for 3 devices placed side-by-side  Correction factor of rating current for 4 and	0.95
devices placed side-by-side  Correction factor of rating current for 3 devices placed side-by-side  Correction factor of rating current for 4 and 5 devices placed side-by-side  Correction factor of rating current for 6	0.95
devices placed side-by-side  Correction factor of rating current for 3 devices placed side-by-side  Correction factor of rating current for 4 and 5 devices placed side-by-side  Correction factor of rating current for 6 devices placed side-by-side  Correction factor of magnetic tripping with	0.95 0.9 0.85
devices placed side-by-side  Correction factor of rating current for 3 devices placed side-by-side  Correction factor of rating current for 4 and 5 devices placed side-by-side  Correction factor of rating current for 6 devices placed side-by-side  Correction factor of magnetic tripping with 100 Hz  Correction factor of magnetic tripping with	0.95 0.9 0.85
devices placed side-by-side  Correction factor of rating current for 3 devices placed side-by-side  Correction factor of rating current for 4 and 5 devices placed side-by-side  Correction factor of rating current for 6 devices placed side-by-side  Correction factor of magnetic tripping with 100 Hz  Correction factor of magnetic tripping with 200 Hz  Correction factor of magnetic tripping with	0.95 0.9 0.85 1.1
devices placed side-by-side  Correction factor of rating current for 3 devices placed side-by-side  Correction factor of rating current for 4 and 5 devices placed side-by-side  Correction factor of rating current for 6 devices placed side-by-side  Correction factor of magnetic tripping with 100 Hz  Correction factor of magnetic tripping with 200 Hz  Correction factor of magnetic tripping with 400 Hz  Correction factor of magnetic tripping with	0.95 0.9 0.85 1.1 1.2
devices placed side-by-side  Correction factor of rating current for 3 devices placed side-by-side  Correction factor of rating current for 4 and 5 devices placed side-by-side  Correction factor of rating current for 6 devices placed side-by-side  Correction factor of magnetic tripping with 100 Hz  Correction factor of magnetic tripping with 200 Hz  Correction factor of magnetic tripping with 400 Hz  Correction factor of magnetic tripping with 60 Hz	0.95 0.9 0.85 1.1 1.2
devices placed side-by-side  Correction factor of rating current for 3 devices placed side-by-side  Correction factor of rating current for 4 and 5 devices placed side-by-side  Correction factor of rating current for 6 devices placed side-by-side  Correction factor of magnetic tripping with 100 Hz  Correction factor of magnetic tripping with 200 Hz  Correction factor of magnetic tripping with 400 Hz  Correction factor of magnetic tripping with 60 Hz	0.95 0.9 0.85 1.1 1.2
devices placed side-by-side  Correction factor of rating current for 3 devices placed side-by-side  Correction factor of rating current for 4 and 5 devices placed side-by-side  Correction factor of rating current for 6 devices placed side-by-side  Correction factor of magnetic tripping with 100 Hz  Correction factor of magnetic tripping with 200 Hz  Correction factor of magnetic tripping with 400 Hz  Correction factor of magnetic tripping with 60 Hz  Dimensions  Depth of installed product	0.95 0.9 0.85 1.1 1.2 1.5 1
devices placed side-by-side  Correction factor of rating current for 3 devices placed side-by-side  Correction factor of rating current for 4 and 5 devices placed side-by-side  Correction factor of rating current for 6 devices placed side-by-side  Correction factor of magnetic tripping with 100 Hz  Correction factor of magnetic tripping with 200 Hz  Correction factor of magnetic tripping with 400 Hz  Correction factor of magnetic tripping with 60 Hz  Dimensions  Depth of installed product  Height of installed product	0.95 0.9 0.85 1.1 1.2 1.5 1 70 mm 83 mm

## Power

Total power loss under IN	8.7 W
Power loss per pole at In	2.93 W
Endurance	
Electric endurance in number of cycles	4000
Number of mechanical operations	20000
Installation, mounting	
Type of top connection for modular devices	with screw
Tightening torque	
Type of top rail clip for modular devices	NA
Type of bottom rail clip for modular devices	metallic
Type of Bottom Connection for modular devices	Blconnect
Top removability for modular devices	No
Bottom removability for modular devices	No
Connection	
Connection cross-sect. flexible conductor	1 / 25mm²
Connection cross-sect. rigid cable	1 / 35mm²
Connection cross-section of input and output with screws, for massive conductors	1 / 35 mm²
Connection cross section of access and exit with screws, for flexible conductor	1 / 25 mm²
Type of connection	with screw
Standards	
Standard text	EN 60898-1
Safety	
REACH conform	No
RoHS conform	Yes
Halogen free	No
Use conditions	
Operating temperature	-2570 °C
Degree of pollution according to IEC 60664 / IEC 60947-2	2
Class of energy limitation I²t	3
Altitude	2000 m
Air humidity protection	for all climates
Storage/transport temperature	-2580 °C
Identification	
Aesthetic for B.G. Protection devices	FD