



6765106084

**Socket outlet w. earthing pin and LED orientation light, Q.x, alu velvety, lacq.**

**Technical characteristics**

**Architecture**

Fixing mode	flush-mounting
Number of poles	2pole + earth

**Configuration**

Number of modules	1
-------------------	---

**Main electrical features**

Nominal voltage	250 V
Rated voltage	250 V AC
Frequency	50/60 Hz
Rated current	16 A

**Dimensions**

Insertion depth	32 mm
-----------------	-------

**Power**

Power consumption	0.25 W/0.35 VA
-------------------	----------------

**Cover, door**

Cover	Central cover plate
-------	---------------------

**Detection**

Sensor	integrated brightness sensor that switches the orientation light on at twilight and off when there is sufficient brightness
--------	---

**Materials**

Colour	aluminium
Colour	aluminium optics
RAL colour	RAL 9006 - White aluminium
Material / workmanship	lacquered
Material	thermoplastic
Surface appearance	velvety

**Lighting control**

Switch-off brightness	4 lx
Switch-on brightness	2 lx
Light intensity (white)	0.2 cd

**LED control**

LED	long service life of the LED, white LED light
-----	---

**Installation, mounting**

Installation mode with spreader claws

**Connection**

Conductor cross-section (rigid) 2.5

Connection terminals according to IEC 60884-1

Type of connection with screw-in lift terminals

**Cable**

Wiring through-wiring possible, therefore also ideal for retrofitting

**Equipment**

Lighting additional benefit by combination of a socket outlet with an orientation light

**Use**

Differentiation characteristic 2 - Sales enhanced contact protection

Differentiation characteristic 3 - Sales Screw-in lift terminals

**Safety**

IK protection code against mechanical impacts 05

Protection Enhanced contact protection

With enhanced contact protection Yes

**Identification**

Main design line Berker Q.1/Q.3/Q.7/Q.9

Secondary design line(s) Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9

**Instructions**

Information text Caution! Items with special flush-mounted insert. Centre plates with LED orientation lights are not compatible with the standard socket outlets.