



85341224

## IR motion detector comfort 1.1 m, Q.x alu velvety, lacquered

### Technical characteristics

#### Architecture

Fixing mode flush-mounting

#### Functions

Function with keylock

#### Controls and indicators

Button / push-button with button for on/off/automatic

#### Dimensions

Assembling height 34 mm

Nominal mounting height 1.1 m

#### Tripping

immunity time  $\approx 10$  s

#### Measurement

Detection field, rectangular shaped  $\approx 12 \times 16$  m

#### Reach distance

Range, frontal  $\approx 12$  m

#### Detection

Number of detection levels 3

Detection angle, settable each side  $\approx 45 \dots 90^\circ$

Detection field  $\varnothing$ , on floor 0 m

#### Materials

Colour aluminium

Material / workmanship lacquered

Material thermoplastic

#### Lighting control

Response brightness, adjustable  $\approx 5 \dots 1000$  lx , daytime operation

#### Settings

Response value luminosity adjustable Yes

Response value sensitivity adjustable Yes

Response sensitivity, settable 10...100 %

Short time mode 200 ms

Delay time  $\approx 180$  s

---

Delay time, adjustable	≈ 10 s...30 mn
------------------------	----------------

---

Switch-off pre-warning to dimming value 50% for	30 s
--	------

---

**Safety**

---

Protection index IP	IP20
---------------------	------

---

Protection	with dismantling protection
------------	-----------------------------

---

**Use conditions**

---

Operating temperature	-5...45 °C
-----------------------	------------

---

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

---

**Identification**

---

Application, usage	Light control, Motion detector
--------------------	--------------------------------

---

Main design line	Berker Q.1/Q.3/Q.7/Q.9
------------------	------------------------

---

Secondary design line(s)	Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9
--------------------------	--

---

**Instructions**

---

Information text	Continuous direct sunlight penetrating the upward-pointing detection plane can result in failure of the motion detector. Only suitable for indoor areas!
------------------	--