



85648182



IP20

KNX radio button 4gang quicklink, S.1, white glossy

Technical characteristics

Functions

	ETS additional functions: +6 scenes, 1 button control up/down, operating mode on/off, dimming value, brightness display, push-button, status display, forced control
ETS additional functions	

	quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory
Quicklink functions	

Connectivity

Radio protocol	KNX Radio
----------------	-----------

Receiver category	2
-------------------	---

Power

Radio transmission power	< 10 mW
--------------------------	---------

Materials

Colour of design line	white
-----------------------	-------

RAL colour	RAL 1013 - Oyster white
------------	-------------------------

Material	thermoplastic
----------	---------------

Equipment

Number of radio channels	4
--------------------------	---

Number of quicklink links	max. 20 transmitter/receiver
---------------------------	------------------------------

Transmitter duty cycle	1 %
------------------------	-----

Safety

Protection	with dismantling protection
------------	-----------------------------

Use conditions

Operating temperature	-5...45 °C
-----------------------	------------

Relative humidity (without condensation)	0...65 % (without condensation)
--	---------------------------------

Identification

Application, usage	Light control, KNX radio- operating systems
--------------------	---

Main design line	Berker S.1/B.3/B.7
------------------	--------------------

Secondary design line(s)	Berker S.1, Berker B.3, Berker B.7
--------------------------	------------------------------------

Instructions

	Extended operating options on 1gang inserts through 2 additional, freely-configurable radio channels.
Information text	