




85648189



IP20

## KNX radio button 4gang quicklink, S.1/B.3/B.7, p. white glossy

### Technical characteristics

#### Functions

	ETS additional functions: +6 scenes, 1 button control up/down, operating mode on/off, dimming value, brightness display, push-button, status display, forced control
ETS additional functions	

Quicklink functions

quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button, memory

#### Connectivity

Radio protocol	KNX Radio
Receiver category	2

#### Power

Radio transmission power	< 10 mW
--------------------------	---------

#### Materials

Colour of design line	polar white
RAL colour	RAL 9010 - Pure white
Material	thermoplastic

#### Equipment

Number of radio channels	4
Number of quicklink links	max. 20 transmitter/receiver
Transmitter duty cycle	1 %

#### Safety

Protection	with dismantling protection
------------	-----------------------------

#### Use conditions

Operating temperature	-5...45 °C
Relative humidity (without condensation)	0...65 % (without condensation)

#### Identification

Application, usage	Light control, KNX radio- operating systems
Main design line	Berker S.1/B.3/B.7
Secondary design line(s)	Berker S.1, Berker B.3, Berker B.7

#### Instructions

	Extended operating options on 1gang inserts through 2 additional, freely-configurable radio channels.
Information text	