



85656288







KNX radio wall-transm. 2gang flat quickl., S.1/B.3/B.7, p.white, matt, plastic

Technical characteristics

			-4		_	-	_
_	ш	ш		ш	O	п	5

ETS additional functions	ETS additional functions: +6 scenes, operating mode on/off, push-button, status display, dimming value
	quicklink functions: switching, dimming, blind, 2 scenes, time switching, NO contact push-button,
Quicklink functions	memory
Connectivity	
Radio protocol	KNX Radio
Receiver category	2
Dimensions	
Assembling height	14 mm
Frequency	
Radio transmission frequency	868.3 MHz
Power	
Radio transmission power	< 10 mW
Battery	
Battery service life [years]	≈ 5
Materials	
Colour of design line	polar white
RAL colour	RAL 9010 - Pure white
Material	thermoplastic
Surface appearance	matt
Equipment	
Number of radio channels	4
Number of quicklink links	max. 20 transmitter/receiver
Transmitter duty cycle	1 %
Safety	
Protection	with dismantling protection
Use conditions	
Operating temperature	-545 °C
Relative humidity (without condensation)	065 % (without condensation)
Identification	
Application, usage	KNX radio- operating systems

Main design line Berker S.1/B.3/B.7

Secondary design line(s)

Berker S.1, Berker B.3, Berker B.7