

HNB160Z

### Moulded Case Circuit Breaker x250 3P 40kA 160A TM

### **Technical characteristics**

Type of order	Toggle
Number of poles	3 P
Type of pole	3P3D
Functions	
Complete device with protection unit	Yes
Trip Unit	TM F/F
With integrated earth leakage fault protection	No
Configuration	
Number of modules	6
Main electrical features	
Rated operational voltage Ue	220 / 415 V
Frequency	50/60 Hz
Voltage	
Rated insulation voltage	800 V
Rated impulse withstand voltage	8 kV
With under voltage release	No
Electric current	
Rated current	160 A
Rated ultimate short-circuit breaking capacity Icu under 690V AC IEC 60947-2	4 kA
Thermal protection nob setting xIN	1
Breaking capacity on 1 pole for IT 230V NF 60947-2	51 kA
Breaking capacity on 1 pole for IT 400V NF 60947-2	9 kA
Rated service breaking capacity Ics AC according IEC 60947-2	50 %
Rated ultimate short-circuit breaking capacity Icu under 230V AC IEC 60947-2	85 kA
Rated ultimate short-circuit breaking capacity Icu under 240V AC IEC 60947-2	85 kA
Rated ultimate short-circuit breaking capacity Icu under 400V AC IEC 60947-2	40 kA
Rated ultimate short-circuit breaking capacity Icu under 415V AC IEC 60947-2	40 kA
Rated ultimate short-circuit breaking capacity Icu under 440V AC IEC 60947-2	30 kA

#### **Current correction factors**

Correction factor of rating current for 2 devices placed side-by-side	1
Correction factor of rating current for 3 devices placed side-by-side	1
Correction factor of rating current for 4 and 5 devices placed side-by-side	1
Correction factor of rating current for 6 devices placed side-by-side	1
Power	
Total power loss under IN	32.6 W
Power loss per pole at In	10.9 W
Tripping	
Tripmode	TM
Thermal protection trip time	0 ms
Time of response when opening	10 ms
Electrical specifications	
Magnetic trip delay time	0 ms
Endurance	
Electric endurance in number of cycles	1000
Number of mechanical operations	4000
Installation, mounting	
DIN rail mounting with optional adaptator	Yes
	105
Connection	
<b>Connection</b> Connection cross-sect. flexible conductor	
	35 / 150mm²
Connection cross-sect. flexible conductor	35 / 150mm² 35 / 185mm²
Connection cross-sect. flexible conductor Connection cross-sect. rigid cable	35 / 150mm² 35 / 185mm² Front connection
Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Connection	35 / 150mm² 35 / 185mm² Front connection
Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Connection Type of connection	35 / 150mm <sup>2</sup> 35 / 185mm <sup>2</sup> Front connection Terminal
Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Connection Type of connection Settings	35 / 150mm <sup>2</sup> 35 / 185mm <sup>2</sup> Front connection Terminal 2080 A
Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Connection Type of connection Settings Range of the magnetic adjustment	35 / 150mm² 35 / 185mm² Front connection Terminal 2080 A 10
Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN	35 / 150mm² 35 / 185mm² Front connection Terminal 2080 A 10
Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith	35 / 150mm <sup>2</sup> 35 / 185mm <sup>2</sup> Front connection Terminal 2080 A 10
Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally	35 / 150mm² 35 / 185mm² Front connection Terminal 2080 A 10 IN
Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally	35 / 150mm <sup>2</sup> 35 / 185mm <sup>2</sup> Front connection Terminal 2080 A 10 IN 0
Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-	35 / 150mm² 35 / 185mm² Front connection Terminal 2080 A 10 IN 0 0
Connection cross-sect. flexible conductor Connection cross-sect. rigid cable Connection Type of connection Settings Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change- over contact	35 / 150mm² 35 / 185mm² Front connection Terminal 2080 A 10 10 10 0 0 0 0 9

# Standards

-35...70 °C

## Standard text

## Safety

Yes
Yes
No
-2570 °C
2000 m
for all climates

Storage/transport temperature