



HNE801H

Moulded Case Circuit Breaker h1000 4P 50kA 800A LSI

Technical characteristics

Architecture	
Number of poles	4 P
Functions	
Complete device with protection unit	Yes
Trip Unit	LSI
Integrated earth fault protection	No
Configuration	
Number of modules	16
Main electrical features	
Rated operational voltage Ue	220 / 690 V
Frequency	50/60 Hz
Voltage	
Rated insulation voltage	800 V
Rated impulse withstand voltage	8 kV
With under voltage release	No
Electric current	
Rated current	800 A
Rated ultimate short-circuit breaking capacity Icu under 690V AC IEC 60947-2	20 kA
Thermal protection nob setting xIN	0.4 / 0.5 / 0.63 / 0.9 / 0.95 / 1
Thermal setting current on neutral pole	0 / 0.5 / 1 ln
Breaking capacity on 1 pole for IT 230V NF 60947-2	51 kA
Breaking capacity on 1 pole for IT 400V NF 60947-2	9 kA
Rated service breaking capacity Ics AC according IEC 60947-2	100 %
Rated ultimate short-circuit breaking capacity Icu under 230V AC IEC 60947-2	85 kA
Rated ultimate short-circuit breaking capacity Icu under 240V AC IEC 60947-2	85 kA
Rated ultimate short-circuit breaking capacity Icu under 400V AC IEC 60947-2	50 kA
Rated ultimate short-circuit breaking capacity Icu under 415V AC IEC 60947-2	50 kA
Rated ultimate short-circuit breaking capacity Icu under 440V AC IEC 60947-2	45 kA

Subject to technical modifications

Current correction factors

devices placed side-by-side	
Correction factor of rating current for 3 devices placed side-by-side	
Correction factor of rating current for 4 and 5 devices placed side-by-side	
Correction factor of rating current for 6 devices placed side-by-side	
Power	
Total power loss under IN	153.6 V
Power loss per pole at In	51.2 \
Tripping	
Tripmode	L
Thermal protection trip time	5 / 10 / 11 / 19 / 21 / 29 m
Time of response when opening	10 m
Electrical specifications	
Magnetic trip delay time	100 to 200 m
Endurance	
Electric endurance in number of cycles	100
Installation, mounting	
DIN rail mounting with optional adaptator	N
Connection	
Type of connection	Termina
Settings	
Settings Range of the magnetic adjustment	4480 / 5600 / 7000 / 8960 / 9600 / 9600 / 9600
Range of the magnetic adjustment	2.5 / 5 / 1
Range of the magnetic adjustment Magnetic protection nob setting xIN	2.5 / 5 / 1
Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith	2.5 / 5 / 1
Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally	2.5 / 5 / 1
Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally	2.5 / 5 / 1
Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-	2.5 / 5 / 1 IrT
Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact	2.5 / 5 / 1 IrT
Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional	2.5 / 5 / 1 IrT
Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional Use cases	2.5 / 5 / 1 IrT
Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional Use cases Category of use	4480 / 5600 / 7000 / 8960 / 9600 / 9600 / 9600 2.5 / 5 / 1 IrT Ye
Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional Use cases Category of use Standards	2.5 / 5 / 1 IrT
Range of the magnetic adjustment Magnetic protection nob setting xIN Setting type In or Ith Equipment Number of auxiliary contacts as normally closed contact Number of auxiliary contacts as normally open contact Number of auxiliary contacts as change-over contact Motor drive optional Use cases Category of use Standards Standard text	2.5 / 5 / 1 IrT Ye

Altitude 2000 m

Storage/transport temperature

-35...70 °C