

 KNX

up/down push-button



TRM692G







Module 1 flush mounted output 3A for shutters or blinds + 2 inputs, KNX radio

Technical characteristics

Architecture					
Bus system					

Number of blinds/shutters outputs

Functions

quicklink functions: blind, 2 scenes, forced control,

Quicklink functions

Configuration

Number of modules 0

Controls and indicators

Indicator lamp yes

Connectivity

Radio protocol	KNX Radio
Receiver category	2

Main electrical features

Type of supply voltage	AC

Frequency 50 Hz

Electric current

Number of entry circuits	2

Maximum switching current 3 A

Frequency

Radio reception frequency 868.3 MHz

Power

Contact rating with 230 V in AC1	690 W
Total power loss under IN	450 mW
Power dissipation per coil	150 mW

Connection

	Number of contacts	1

Type of connection

with screw-in lift terminals

Settings

Lamella adjustment on signal duration

< 1 s

Equipment				
Number of quicklink links	max. 20 transmitter/receiver			
Self-retaining for 2 min on signal length	> 1 s			
Transmitter duty cycle	1 %			
Change-over time for change of direction	< 0.6 s			
Use conditions				
Operating temperature	-1050 °C			
Storage/transport temperature	-2070 °C			

0...65 % (without condensation)

Relative humidity (without condensation)