



JK240MID

## JK Multifunction Meter Pack 250A Pulsed and Modbus MID

## **Technical characteristics**

| Type of pole                           | 3P+N                     |
|--|--------------------------|
| Electric current                       |                          |
| Rated current                          | 250 A                    |
| Maximum measuring circuit current      | 6,000 A                  |
| Capacity                               |                          |
| Number of modules                      | 4                        |
| Dimensions                             |                          |
| Height                                 | 118.50 mm                |
| Width                                  | 70 mm                    |
| Depth                                  | 66 mm                    |
| Installation, mounting                 |                          |
| Mounting on                            | DIN rail, Mounting plate |
| Measurement                            |                          |
| Measuring system                       | Measurement transformer  |
| Type of measuring instrument           | Digital                  |
| Current measurement range              | 5 - 6,000 A              |
| Frequency measuring range              | 50 - 50 Hz               |
| Power supply                           |                          |
| Number of phases for power supply      | 3                        |
| Functions                              |                          |
| Accuracy class                         | 1                        |
| Tariff type                            | Multi-tarifi             |
| Is calibrated                          | Yes                      |
| Use conditions                         |                          |
| Operating temperature                  | -10 - 55 °C              |
| Storage/transport temperature          | -20 - 75 °C              |
| Frequency                              |                          |
| ······································ |                          |