



EE806



**IP30**

## Remote control for IP55 motion detector comfort EE86/87

### Technical properties

#### Configuration

Module	télécommande
--------	--------------

#### Compatibility

Sensors associated	EE85x,EE86x,EE87x
--------------------	-------------------

#### Controls and indicators

Operation	3 configuration ranges for control, switch-off delay, brightness threshold
-----------	--

#### Dimensions

Height of installed product	10 mm
Length	111 mm
Dimensions (LLxwwxhh)	120x70x10mm
Width of installed product	63 mm

#### Battery

Battery service life [years]	≈ 5
Number and type of replacement batteries	1x 3V CR2032

#### Detection

IR	RC6 code
----	----------

#### Materials

Colour	black
--------	-------

#### LED control

LED	additional acknowledgement LED for displaying the IR transmission
-----	---

#### Settings

Setting	setting of the brightness threshold manually, by default values or teach-in mode ; default settings can be selected for the brightness threshold daylight, office, corridor
---------	---

#### Accessories included

Accessory type	Manual transmitter for movement sensor
----------------	--

#### Safety

REACH conform	Yes
RoHS conform	Yes

#### Identification

Application, usage	Motion detector ; KNX - sensors
Main design line	Motion detectors