



## HA406

## Load break switch with visible breaking 4P 125A

## **Technical properties**

Arc	h	it	ec	tu	re
-----	---	----	----	----	----

Type of order	Short thumb-grip
Number of poles	4 P
Type of pole	4 P
Type of case	Fixed built-in
Functions	
Reversing switch	No
Configuration	
Number of modules	6
Controls and indicators	
Motor drive integrated	No
Main electrical features	
Rated operational voltage Ue	380 / 415 V
Frequency	50 Hz
Voltage	
Rated insulation voltage	800 V
Rated impulse withstand voltage	8000 V
Electric current	
Rated operational current in AC21category B	125 A
Acceptable current rating with AC22 category A	125 A
Cut off current	15 kA
Rated current	125 A
Short-circuit current with gl-gG fuses	50 kA
Rated short-time withstand current 1s	2.5 kA
Rated operational current in AC21 category A	125 A
Acceptable current rating with AC22 category B	125 A
Rated operational current in AC23 category A	63 A
Acceptable current rating with AC23 category B	63 A
Dimensions	
Width of installed product	108 mm

Power	
Active power under 380/415 V, 50 Hz	45 kW
Total power loss under IN	17.1 W
Power loss per pole at In	5.7 W
Contact rating with 400 V in AC1	82 kW
Cover, door	
Interlockable	Yes
Installation, mounting	
Tightening torque	6 - 6.6 Nm
Fixation type	DIN rail monting or back plate monting
Connection	
Connection cross-sect. rigid cable	50mm² max.
Equipment	
Number of auxiliary contacts as normally closed contact	0
Number of auxiliary contacts as normally open contact	0
Number of auxiliary contacts as change- over contact	0
Motor drive optional	No
Standards	
European directive WEEE	concerned
Safety	
Protection index IP	IP20
REACH conform	Yes
RoHS conform	Yes
Halogen free	No
Use conditions	

-20...70 °C

Operating temperature