



SCHUKO soc.out. LEDorient.,enhncd contact prot.,screw-in lift term.,R.cl,bl.

Technical properties

Design	according to DIN 49440
Fixing mode	flush-mounting
Configuration	
Number of modules	1
Main electrical features	
Nominal voltage	250 V
Rated voltage	250 V AC
Frequency	50/60 Hz
Rated current	16 A
Electric current	
Rated current	16 A
Dimensions	
Insertion depth	32 mm
Power	
Power consumption	0.25 W/0.35 VA
Cover, door	
Cover	Central cover plate
Detection	
Sensor	integrated brightness sensor that switches the orientation light on at twilight and off when there is sufficient brightness
Materials	
Colour of labelling	217,217,217
Colour of design line	black
Colour	black
Colour	deep black
RAL colour	RAL 9005 - Jet black
Material	thermoplastic
Material for printing	PC-PMA black
Lighting control	
Switch-off brightness	≈ 4 lx
Switch-on brightness	≈ 2 lx

LED control

LED white LED light, long service life of the LED

Installation, mounting

Installation mode with spreader claws

Connection

 Conductor cross-section (rigid)
 2.5

 Connection terminals
 according to IEC 60884-1

 Connection terminals
 according to VDE 0620-1

 Type of connection
 with screw-in lift terminals

Cable

through-wiring possible, therefore also ideal for Wiring retrofitting

Settings

Shading parameter R1_czarny
Laser parameter R1_schwarz

Equipment

Type of configuration

Laserdruck

additional benefit by combination of a socket outlet
Lighting with an orientation light

Use

Differentiation characteristic 2 - Sales enhanced contact protection

Differentiation characteristic 3 - Sales Screw-in lift terminals

Safety

Protection index IP IP20
REACH conform Yes
RoHS conform Yes
Halogen free No
Protection Enhanced contact protection
With enhanced contact protection Yes

Identification

Main design line Serie R.classic

Instructions

Note: When integrating this product into the Serie 1930, the 1gang frame for centre plate Ø 58 mm, order no.: 1382 0... may only be used. Installation in multiple combinations of the Serie 1930 is not Special note text possible!

Caution! Items with special flush-mounted insert. Centre plates with LED orientation lights are not compatible with the standard socket outlets.

Information text