



41092089

${\bf SCHUKO\ soc.out.\ LEDorient.,} enh ncd\ contact\ prot., screw-in\ lift\ term., R. classic, wh$

Technical properties

Design	according to DIN 49440
Fixing mode	flush-mounting
Configuration	
Number of modules	1
Main electrical features	
Nominal voltage	250 V
Rated voltage	250 V AC
Frequency	50/60 Hz
Rated current	16 A
Electric current	
Rated current	16 A
Dimensions	
Insertion depth	32 mm
Power	
Power consumption	0.25 W/0.35 VA
Cover, door	
Cover	Central cover plate
Detection	
	integrated brightness sensor that switches the orientation light on at twilight and off when there is
Sensor	sufficient brightness
Materials	
Colour of labelling	105,105,105
Colour of design line	polar white
Colour	polarwhite
Colour	white
Material for printing	ASA polar white
Lighting control	
Switch-off brightness	≈ 4 lx
Switch-on brightness	≈ 2 lx
Light intensity (white)	0.2 cd

LED control LED white LED light; long service life of the LED Installation, mounting Installation mode with spreader claws Connection max. 2.5 mm² Conductor cross-section (rigid) Connection terminals according to IEC 60884-1 Connection terminals according to VDE 0620-1 Cable through-wiring possible, therefore also ideal for Wiring retrofitting **Settings** R1_biały Shading parameter Laser parameter R1_weiß **Equipment** Type of configuration Laserdruck Use Differentiation characteristic 2 - Sales enhanced contact protection Differentiation characteristic 3 - Sales Screw-in lift terminals Safety Protection index IP IP20 REACH conform Yes RoHS conform Yes Halogen free No Protection Enhanced contact protection With enhanced contact protection Yes Identification Main design line Serie 1930/R.classic Secondary design line(s) Serie 1930; Series R.classic Instructions Note: When integrating this product into the Serie 1930, the 1gang frame for centre plate Ø 58 mm, order no.: 1382 0... may only be used. Installation in multiple combinations of the Serie 1930 is not Special note text possible! Caution! Items with special flush-mounted insert. Centre plates with LED orientation lights are not

compatible with the standard socket outlets.

Information text