



41097006

${\bf SCHUKO\ soc.out.\ LEDorient.,} enh ncd\ contact\ prot., screw-in\ lift\ term., K1, ant., lacq$

Technical properties

Architecture	
Design	according to DIN 49440
Fixing mode	flush-mounting
Configuration	
Number of modules	1
Main electrical features	
Nominal voltage	250 V
Rated voltage	250 V AC
Frequency	50/60 Hz
Rated current	16 A
Electric current	
Rated current	16 A
Dimensions	
Insertion depth	32 mm
Power	
Power consumption	0.25 W/0.35 VA
Cover, door	
Cover	Central cover plate
Detection	
Sensor	integrated brightness sensor that switches the orientation light on at twilight and off when there is sufficient brightness
Materials	
Colour of design line	anthracite
Colour	anthracite
Material / workmanship	lacquered
Surface appearance	matt
Lighting control	
Switch-off brightness	≈ 4 lx
Switch-on brightness	≈ 2 lx
Light intensity (white)	0.2 cd

п	\Box

Installation mode	with spreader claws
Connection	
Conductor cross-section (rigid)	max. 2.5 mm²
Connection terminals	according to IEC 60884-1
Connection terminals	according to VDE 0620-1
Cable	
Wiring	through-wiring possible, therefore also ideal for retrofitting
Use	
Differentiation characteristic 2 - Sales	enhanced contact protection
Differentiation characteristic 3 - Sales	Screw-in lift terminals
Safety	
IK protection code against mecanical impacts	05
Protection index IP	IP20
REACH conform	Yes
RoHS conform	Yes
Halogen free	No
Protection	Enhanced contact protection
With enhanced contact protection	Yes

Identification

Main design line Berker K.1

Instructions

Caution! Items with special flush-mounted insert. Centre plates with LED orientation lights are not compatible with the standard socket outlets.

Information text