



75161592



IP20

## B.IQ push-button 1gang comf, KNX - B.IQ, glass black

### Technical properties

#### Functions

With room temperature controller	No
----------------------------------	----

Function	for switch, push-button, dimmer and shutter functions
----------	---

#### Compatibility

Extension unit	extension unit for light scene push-button
----------------	--

#### Controls and indicators

With LED indication	Yes
---------------------	-----

Number of buttons	1
-------------------	---

Operation	activation of second user level via object ; one push-button operation for switching, pushing, shutters and dimming
-----------	---

#### Dimensions

Assembling height	16.7 mm
-------------------	---------

Height	88.5 mm
--------	---------

Width	88.5 mm
-------	---------

#### Measurement

Value transmitter	value transmitter for dimming, position, brightness and temperature values 1 and 2 byte
-------------------	---

#### Screen

With display	No
--------------	----

#### Materials

Colour of design line	glass black
-----------------------	-------------

Surface appearance	glossy
--------------------	--------

#### LED control

LED	with blue operation LED and 2 white status LEDs (labelling field illumination)
-----	--

#### Connection

Bus coupling unit	for bus coupling unit flush-mounted
-------------------	-------------------------------------

#### Settings

Supported configuration modes	system, PB
-------------------------------	------------

Parameterisation	single and two push-button operation parameterisable
------------------	--

#### Scope of delivery

Bus connection included	No
<b>Accessories included</b>	
Box	for installation in single standard wall boxes
Matching products	for additional products to complement the installation in matching colours/materials, refer to the Design platform S.1/B.x ; for glass frames in the same "style" for additional applications, see the Design line B.7
<b>Equipment</b>	
Number of actuation points	2
With anti-theft/dismantling protection	Yes
Product type:	product type: B.IQ
<b>Safety</b>	
REACH conform	Yes
RoHS conform	Yes
Protection	with dismantling protection
Alarm	alarm telegram after disconnection from bus coupling unit 1 bit or 1 byte
<b>Use conditions</b>	
Operating temperature	-5...45 °C
<b>Identification</b>	
Application, usage	KNX - operating systems
Product family	product family: push-button
Main design line	KNX - Berker B.IQ
Secondary design line(s)	KNX ; Berker B.IQ