



75161592



**IP20**

## B.IQ push-button 1gang comf, KNX - B.IQ, glass black

### Technical properties

#### Functions

With room temperature controller	No
----------------------------------	----

Function	for switch, push-button, dimmer and shutter functions
----------	---

#### Compatibility

Extension unit	extension unit for light scene push-button
----------------	--

#### Controls and indicators

With LED indication	Yes
---------------------	-----

Number of buttons	1
-------------------	---

Operation	activation of second user level via object ; one push-button operation for switching, pushing, shutters and dimming
-----------	---

#### Dimensions

Assembling height	16.7 mm
-------------------	---------

Height	88.5 mm
--------	---------

Width	88.5 mm
-------	---------

#### Measurement

Value transmitter	value transmitter for dimming, position, brightness and temperature values 1 and 2 byte
-------------------	---

#### Screen

With display	No
--------------	----

#### Materials

Colour of design line	glass black
-----------------------	-------------

Surface appearance	glossy
--------------------	--------

#### LED control

LED	with blue operation LED and 2 white status LEDs (labelling field illumination)
-----	--

#### Connection

Bus coupling unit	for bus coupling unit flush-mounted
-------------------	-------------------------------------

#### Settings

Supported configuration modes	system, PB
-------------------------------	------------

Parameterisation	single and two push-button operation parameterisable
------------------	--

#### Scope of delivery

Bus connection included

No

### Accessories included

Box for installation in single standard wall boxes

Matching products

for additional products to complement the installation in matching colours/materials, refer to the Design platform S.1/B.x ; for glass frames in the same "style" for additional applications, see the Design line B.7

### Equipment

Number of actuation points 2

With anti-theft/dismantling protection Yes

Product type: product type: B.IQ

### Safety

REACH conform Yes

RoHS conform Yes

Protection with dismantling protection

Alarm alarm telegram after disconnection from bus coupling unit 1 bit or 1 byte

### Use conditions

Operating temperature -5...45 °C

### Identification

Application, usage KNX - operating systems

Product family product family: push-button

Main design line KNX - Berker B.IQ

Secondary design line(s) KNX ; Berker B.IQ