




75164780



## Berker S.1/B.3/B.7 Push Button 4-gang, Comfort with Label, White and Polar White

### Technical properties

#### Functions

With room temperature controller No

Function for switch, push-button, dimmer and shutter functions

#### Compatibility

Extension unit extension unit for light scene push-button

#### Controls and indicators

With LED indication Yes

Number of buttons 4

Operation one push-button operation for switching, pushing, shutters and dimming ; lockable via 3-button actuation ; second operating level via object or 3-button handle

#### Dimensions

Labelling field length (W x H) 52.3 x 24.9 mm

Height 110.7 mm

Width 56 mm

#### Measurement

Value transmitter value transmitter for dimming, position, brightness and temperature values 1 and 2 byte

#### Screen

With display No

#### Materials

Colour of labelling 105,105,105

Colour of design line white/polar white

Colour independent of design lines for white and polar white

Material for printing Paper

Surface appearance glossy

Type of surface treatment untreated

Material family Plastic

#### LED control

LED with white operation LED and 8 red status LEDs

#### Connection

Bus coupling unit for bus coupling unit flush-mounted

---

**Settings**

Parameterisation single and two push-button operation parameterisable

---

**Scope of delivery**

Bus connection included No

---

**Equipment**

Number of actuation points 8

With anti-theft/dismantling protection Yes

Type of configuration Beschriftungsfeld(er) - Folie

Product type: product type: push-button 4gang

---

**Use**

Differentiation characteristic 1 - Sales with labelling fields

Differentiation characteristic 3 - Sales with horizontal operation

---

**Safety**

Protection with dismantling protection

Alarm alarm telegram after disconnection from bus coupling unit 1 bit or 1 byte

---

**Use conditions**

Operating temperature -5...45 °C

---

**Identification**

Application, usage KNX - operating systems

Product family product family: push-button

Secondary design line(s) KNX ; Berker S.1 ; Berker B.3 ; Berker B.7

---

**Instructions**

Special note text Use only in combination with frame frame with large cut-out.