




75663693



B.IQ IR Push Button with Thermostat, 3-Gang, Brushed Stainless Steel

Technical properties

| Fixing pands | fluck manusting |
|---------------------------|--|
| Fixing mode | flush-mounting |
| Functions | |
| Function | with valve protection function |
| Timers | with room temperature timer and 2-week timer functions |
| Compatibility | |
| Extension unit | extension unit for light scene push-button |
| Controls and indicators | |
| Number of buttons | 3 |
| Operation | one push-button operation for switching, pushing, shutters and dimming |
| Dimensions | |
| Height | 128.6 mm |
| Width | 88.5 mm |
| Measurement | |
| Value transmitter | value transmitter for dimming, position, brightness and temperature values 1 and 2 byte |
| Materials | |
| Colour of design line | Stainless steel |
| RAL colour | RAL 9022 - Pearl light grey |
| Material / workmanship | metal brushed |
| Material | stainless steel |
| Surface appearance | matt |
| Type of surface treatment | brushed |
| LED control | |
| LED | with blue operation LED and 6 white status LEDs (labelling field illumination) |
| Settings | |
| Parameterisation | single and two push-button operation parameteris- able |
| Scope of delivery | |
| Bus connection included | No |

Accessories included

| Box | for installation in single standard wall boxes |
|----------------------------|---|
| | for stainless steel frames in the same "style" for additional applications, see the Design line B.7, for additional products to complement the installation in matching colours/materials, refer to the Design plat- |
| Matching products | form S.1/B.x |
| Equipment | |
| Number of actuation points | 8 |
| Product type: | product type: B.IQ |
| Control | for individual single room temperature control |
| Software | |
| Update | with flash-controller technology |
| Safety | |
| Protection | with dismantling protection |
| Use conditions | |
| Operating temperature | -545 °C |
| Energy efficiency class | IV (2%) |
| Identification | |
| Application, usage | KNX - operating systems |
| Product family | product family: push-button |
| Release issue | 2.6 |
| Main design line | KNX - Berker B.IQ |
| Secondary design line(s) | Berker B.IQ, KNX |
| Instructions | |
| Information text | IR hand-held transmitter, order no. 2779 |