



75664591



**Technical properties**

**Functions**

With room temperature controller	Yes
Function	with valve protection function
Timers	with room temperature timer and 2-week timer functions

**Compatibility**

Extension unit	extension unit for light scene push-button
----------------	--

**Controls and indicators**

With LED indication	Yes
Number of buttons	4
Operation	one push-button operation for switching, pushing, shutters and dimming

**Dimensions**

Width of rail mounted device (RMD)	0 modules
Height	149.2 mm
Width	88.5 mm

**Measurement**

Value transmitter	value transmitter for dimming, position, brightness and temperature values 1 and 2 byte
-------------------	---

**Screen**

With display	Yes
--------------	-----

**Materials**

Colour of design line	glass polar white
RAL colour	RAL 9010 - Pure white
Material	glass
Material family	Glass

**LED control**

LED	with blue operation LED and 8 white status LEDs (labelling field illumination)
-----	--

**Settings**

Parameterisation	single and two push-button operation parameterisable
------------------	--

**Accessories included**

Box	for installation in single standard wall boxes
-----	--

for additional products to complement the installation in matching colours/materials, refer to the Design platform S.1/B.x, for glass frames in the same "style" for additional applications, see the Design line B.7

Matching products

---

**Equipment**

---

Number of actuation points	10
Product type:	product type: B.IQ
Control	for individual single room temperature control

---

**Software**

---

Update	with flash-controller technology
--------	----------------------------------

---

**Safety**

---

Protection	with dismantling protection
------------	-----------------------------

---

**Use conditions**

---

Operating temperature	-5...45 °C
Energy efficiency class	IV (2%)

---

**Identification**

---

Application, usage	KNX - operating systems
Product family	product family: push-button
Release issue	2.5
Main design line	KNX - Berker B.IQ
Secondary design line(s)	KNX, Berker B.IQ