



## HNB251U

## Moulded Case Circuit Breaker X250 4P 40kA 250A TM

## **Technical properties**

Number of poles	4 P
Functions	
Complete device with protection unit	Yes
Trip Unit	TM A/A
Integrated earth fault protection	No
Configuration	
Number of modules	8
Main electrical features	
Rated operational voltage Ue	220 / 415 V
Frequency	50/60 Hz
Voltage	
Rated insulation voltage	800 V
Rated impulse withstand voltage	8 kV
Electric current	350.4
Rated current	250 A
Rated ultimate short-circuit breaking capa- city Icu under 690V AC IEC 60947-2	4 kA
Thermal protection nob setting xIN	0.63 / 0.8 / 1
Thermal setting current on neutral pole	1 In
Breaking capacity on 1 pole for IT 230V NF 60947-2	51 kA
Breaking capacity on 1 pole for IT 400V NF 60947-2	9 kA
Rated service breaking capacity Ics AC according IEC 60947-2	50 %
Rated ultimate short-circuit breaking capa- city Icu under 230V AC IEC 60947-2	85 kA
Rated ultimate short-circuit breaking capa- city Icu under 240V AC IEC 60947-2	85 kA
Rated ultimate short-circuit breaking capa- city Icu under 400V AC IEC 60947-2	40 kA
Rated ultimate short-circuit breaking capa- city Icu under 415V AC IEC 60947-2	40 kA
Rated ultimate short-circuit breaking capa-	
city Icu under 440V AC IEC 60947-2	30

## **Current correction factors**

Correction factor of rating current for 2 devices placed side-by-side	
Correction factor of rating current for 3 devices placed side-by-side	
Correction factor of rating current for 4 and 5 devices placed side-by-side	
Correction factor of rating current for 6 devices placed side-by-side	
Power	
Total power loss under IN	48 \
Power loss per pole at In	16 \
Tripping	
Tripmode	Т
Thermal protection trip time	0 m
Time of response when opening	10 m
Electrical specifications	
Magnetic trip delay time	0 m
Endurance	
Electric endurance in number of cycles	100
Installation, mounting  DIN rail mounting with ontional adaptator	Ye
DIN rail mounting with optional adaptator	Υe
DIN rail mounting with optional adaptator  Connection	35 / 150mn
DIN rail mounting with optional adaptator  Connection  Connection cross-sect. flexible conductor	35 / 150mn
Connection  Connection  Connection cross-sect. flexible conductor  Type of connection	35 / 150mn Termin
Connection  Connection  Connection cross-sect. flexible conductor  Type of connection  Settings	35 / 150mn Termin 1250 / 1750 / 2250 / 2750
Connection  Connection  Connection cross-sect. flexible conductor  Type of connection  Settings  Range of the magnetic adjustment	35 / 150mn Termin 1250 / 1750 / 2250 / 2750 5 / 7 / 9 / 1
Connection  Connection  Connection cross-sect. flexible conductor  Type of connection  Settings  Range of the magnetic adjustment  Magnetic protection nob setting xIN	35 / 150mn Termin 1250 / 1750 / 2250 / 2750 5 / 7 / 9 / 1
Connection  Connection  Connection cross-sect. flexible conductor  Type of connection  Settings  Range of the magnetic adjustment  Magnetic protection nob setting xIN  Setting type In or Ith	35 / 150mn Termin 1250 / 1750 / 2250 / 2750 5 / 7 / 9 / 1
Connection  Connection  Connection cross-sect. flexible conductor  Type of connection  Settings  Range of the magnetic adjustment  Magnetic protection nob setting xIN  Setting type In or Ith  Equipment  Number of auxiliary contacts as normally	35 / 150mn Termin 1250 / 1750 / 2250 / 2750 5 / 7 / 9 / 1
Connection  Connection  Connection cross-sect. flexible conductor  Type of connection  Settings  Range of the magnetic adjustment  Magnetic protection nob setting xIN  Setting type In or Ith  Equipment  Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally	35 / 150mn Termin 1250 / 1750 / 2250 / 2750 5 / 7 / 9 / 1
Connection  Connection  Connection cross-sect. flexible conductor  Type of connection  Settings  Range of the magnetic adjustment  Magnetic protection nob setting xIN  Setting type In or Ith  Equipment  Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-	35 / 150mn  Termin.  1250 / 1750 / 2250 / 2750  5 / 7 / 9 / 1
Connection  Connection  Connection cross-sect. flexible conductor  Type of connection  Settings  Range of the magnetic adjustment  Magnetic protection nob setting xIN  Setting type In or Ith  Equipment  Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact	35 / 150mn  Termin  1250 / 1750 / 2250 / 2750  5 / 7 / 9 / 1
Connection  Connection  Connection cross-sect. flexible conductor  Type of connection  Settings  Range of the magnetic adjustment  Magnetic protection nob setting xIN  Setting type In or Ith  Equipment  Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Motor drive optional	35 / 150mn  Termin  1250 / 1750 / 2250 / 2750  5 / 7 / 9 / 1
Connection  Connection  Connection cross-sect. flexible conductor  Type of connection  Settings  Range of the magnetic adjustment  Magnetic protection nob setting xIN  Setting type In or Ith  Equipment  Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Motor drive optional  Use cases	35 / 150mn  Termin.  1250 / 1750 / 2250 / 2750  5 / 7 / 9 / 1
Connection  Connection  Connection cross-sect. flexible conductor  Type of connection  Settings  Range of the magnetic adjustment  Magnetic protection nob setting xIN  Setting type In or Ith  Equipment  Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Motor drive optional  Use cases  Category of use	35 / 150mm Termin:  1250 / 1750 / 2250 / 2750  5 / 7 / 9 / 1
Connection  Connection  Connection cross-sect. flexible conductor  Type of connection  Settings  Range of the magnetic adjustment  Magnetic protection nob setting xIN  Setting type In or Ith  Equipment  Number of auxiliary contacts as normally closed contact  Number of auxiliary contacts as normally open contact  Number of auxiliary contacts as change-over contact  Motor drive optional  Use cases  Category of use  Standards	35 / 150mm Termina  1250 / 1750 / 2250 / 2750  5 / 7 / 9 / 1

REACH conform	Yes
RoHS conform	Yes
Use conditions	
Operating temperature	-2570 °C
Altitude	2000 m
Storage/transport temperature	-3570 °C