



TXA207C

Output 10 -fold 16A

Technical properties

Architecture	

Functions

Configuration

Number of modules	

Controls and indicators

ves	Indicator lamp

Main electrical features

Rated operational voltage Ue	230 V	
Rated current	16 A	

Voltage

Operating voltage over bus	2132 V DC
Output voltage	230 V~
System supply voltage	30V DC via bus

Electric current

Number of entry circuits	0
Maximum through current	16 A
Rated current	16.Δ

Power

Max. power with electronic transfo.	1200 W
Total power loss under IN	15 W
Output power	2300 W
Max. switching power	14375 W

Fluorescent bulbs control

Max	nower fluo duo	lamp comp. series	20 x 36 W
I-IUA.	power mao, ado	idilip collip. Sciles	20 X 30 W

Incandescent bulbs control

Max. power with incandescent lamps	2300 W
------------------------------------	--------

Connection

Connection cross-sect. flexible conductor	0,75 / 2,5mm ²
Connection cross-sect. rigid cable	0,75 / 2.5mm ²

Type of contacts	10NO
Bus coupling unit	with integral bus coupling unit
Bus connection	bus connection via connecting terminal
Type of connection	quick connect
Scope of delivery	
Bus connection included	Yes
Equipment	
Number of outputs	10
Bidirectional radio frequency	No
Modular expandability	No
Use conditions	
Operating temperature	045 °C
Storage/transport temperature	-2070 °C
Identification	
Main design line	KNX