



TXC511





EIB presence detector with Light Regulation

Technical properties

Λ	rc	hi	ite	0	tu	ıre

Bus system		KNX

Connectivity

Number of binary inputs 0

Voltage

Operating voltage over bus 21...32 V DC

Electric current

Bus current consumption (data transfer)	12 mA
Bus current consumption (idle)	12 mA

Dimensions

Dimensions (Ø x H)	110 x 44 mm
Recommended installation height	2.53.5 m

Measurement

Detection Method presence

Detection

Detection angle	360 °
Angle of vertical detection	55 °
Frontal detecting distance	7 m
Side detecting distance	6 m

Materials

Colour	wnite
RAL colour	RAL 9010 - Pure white
Surface appearance	matt

Lighting control

Brightness measurement range 5 / 1200 Lux

Installation, mounting

Maximum Mounting Height	4 m
Installation mode	for ceiling mounting in 60 surface-mounted or hollow-wall box

Connection

Bus coupling unit	with integral bus coupling unit
Bus connection	bus connection via connecting terminal

Settings	
Supported configuration modes	system, easy
Delay time, adjustable	≈ 130 mn
Setting	with potentiometers for setting the response bright- ness and delay time without dismantling
Scope of delivery	
Bus connection included	Yes
Equipment	
Number of channels	1
Angle of horizontal detection	360 °
Slewing	Detector head slewing by 90°
Use conditions	
Operating temperature	045 °C
Storage/transport temperature	-1060 °C
Energy-saving	energy saving by presence and brightness-con- trolled lighting control
Identification	

KNX

Main design line