







Fancoil 2 outputs 10A, hand status, KNX

Architecture	
Fixing mode	REG
Functions	
Fan convectors	for the electric activation of fan convectors, activation of 1 or 2 fan channels with 6 or 3 fan stages, for converting RTR control variables into valve positions, fan stages, manual activation of blow fansusing push-buttons or the operating panel, 4 manua operation buttons for controlling fan stages and but function on/of
Multi-phase mode	suitable to switch different external conductors
Operating mode	Operating modes heating, cooling or heating and cooling
Configuration	
Channels	use of free channels to control switching loads
Number of modules	4
Controls and indicators	
Operation	manual operation also possible without bus, e.g. on building site
Button / push-button	with programming button and red programming LED
Main electrical features	
Frequency	50/60 Hz

Voltage	
Auxiliary voltage	230 V AC
Operating voltage over bus	2132 V DC
System supply voltage	30V DC via bus

Dimensions	
Depth	70 mm
Assembling height as from DIN rail	63 mm
Width of rail mounted device (RMD)	4 modules

Height	90 mm
Width	72 mm

Power	
Fluorescent lamps duo circuit	2300 W
Power consumed	0.15 W
Power consumption, KNX	max. 150 mW
Total power loss under IN	3 W

Conventional transformers	1200 VA	
Electronic transformers	1500 V	
Materials		
Colour independent of design lines	light gre	
Colour	light gre	
RAL colour	RAL 7035 - Light gre	
Lighting control		
- uncompensated	1000 V	
Fluorescent bulbs control		
Fluorescent lamps parallel compensated	1160 V	
LED control		
LED	with 8 red status LEDs and 3 red LEDs as manua actuation indication	
Incandescent bulbs control		
230 V incandescent lamps	2300 V	
230 V halogen lamps	2300 V	
Installation, mounting		
Mounting type	din-Ra	
Connection		
Connection cross-sect. flexible conductor	0,75 / 4mm	
Connection cross-sect. rigid cable	1,5 / 4mm	
Conductor cross-section (flexible)	0.54 mm	
Type of connection to the bus	TG008 connecto	
Bus coupling unit	with integral bus coupling un	
Type of connection	with screw terminal	
Bus connection	bus connection via connecting termina	
Terminal type of the outputs	Cage terminals with screv	
Settings		
Supported configuration modes	syster	
Safety		
Protection index IP	IP2	
REACH conform	Ye	
RoHS conform	Ye	
Use conditions		
Operating temperature	-545 °ı	
Storage/transport temperature	-2570 °C (storage at > 45°C reduces the service life)	
Identification		
Main design line	KN	

Comply with	the	fan	convector	manufacturer's
				instructions.