



10107100

Sealing set for switches/push-buttons, K.x/Q.x, trans.

Technical properties

Controls and indicators

| | |
|----------------------------------|--|
| Push-buttons | also for KNX applications: push-button, 1gang, and group push-button, 1gang |
| Rocker switch/rocker push-button | for change-over/intermediate switch and on/off switch, 2-pole, 10 AX ; for rocker push-buttons |

Materials

| | |
|------------------------------------|-------------|
| Colour independent of design lines | transparent |
|------------------------------------|-------------|

Scope of delivery

| | |
|-----------|--------------------------------------|
| Component | with IP44 fixing element to screw on |
|-----------|--------------------------------------|

Use cases

| | |
|-------------|---------------|
| Application | Light control |
|-------------|---------------|

Safety

| | |
|---------------|-----|
| REACH conform | Yes |
| RoHS conform | Yes |
| Halogen free | No |

Identification

| | |
|--------------------------|--|
| Application, usage | Flush-mounted wet-room installation |
| Main design line | Berker K.x/Q.x |
| Secondary design line(s) | Berker Q.1 ; Berker Q.3 ; Berker Q.7 ; Berker K.1 ; Berker K.5 |