



16616049

Rocker f. access. const., guide f. mouth-held rod, lens, Q.1/Q.3, p.white velv.

## **Technical properties**

| Push-buttons                             | also for KNX applications: push-button, 1gang, and<br>group push-button, 1gang |
|--|--|
| Rocker switch/rocker push-button         | for change-over/intermediate switch, for rocke<br>push-buttons                 |
| Materials                                |  |
| Colour of design line                    | polar white  |
| Colour                                   | polarwhite   |
| Colour                                   | white  |
| RAL colour                               | RAL 9010 - Pure white  |
| Material                                 | duroplastic  |
| Surface appearance                       | velvety  |
| Installation, mounting                   |  |
| Installation mode                        | clamp fastening  |
| Equipment                                |  |
| Lighting                                 | for lighting and monitoring circui   |
| Use cases                                |  |
| Barrier-free building                    | based on DIN 18040   |
| Application                              | Barrier-free application, Light contro   |
| Use                                      |  |
| Differentiation characteristic 1 - Sales | with guide for mouth-held roo  |
| Differentiation characteristic 2 - Sales | Lens   |
| Safety                                   |  |
| REACH conform                            | Ye   |
| RoHS conform                             | Yes  |
| Identification                           |  |
| Application, usage                       | Flush-mounted wet-room installation  |
| Main design line                         | Berker Q.1/Q.3/Q.7/Q.9   |
| Secondary design line(s)                 | Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9                                 |
| Instructions                             |  |

The IP44 degree of protection can only be achieved in conjunction with the appropriate neon, incandescent or LED lamp unit, as well as a sealing set for switches/push-buttons.

Special note text