



28806086

Radio Touch and loudspeaker Q.1/Q.3 anthracite, velvety

Technical properties

Functions

| | |
|----------|--|
| Function | volume control ; countdown ; sleep timer ; alarm clock with snooze function |
|----------|--|

Compatibility

| | |
|------------------|---------------------|
| For loudspeakers | per channel 4...8 Ω |
|------------------|---------------------|

Controls and indicators

| | |
|----------------------|---|
| Operation | operation via sensor areas of the touch display |
| Indication / display | Time and date display ; illuminated touch graphics display |

Connectivity

| | |
|--------------------------|----------------------------------|
| Reception / transmission | stereo FM radio with RDS display |
| Inputs | external audio input AUX IN |

Dimensions

| | |
|-------------------------------|------------|
| Insertion depth | 33 mm |
| Dimensions of display (W x H) | 35 x 28 mm |
| Height | 70.8 mm |
| Width | 141.6 mm |

Frequency

| | |
|-----------------------------------|----------------|
| Frequency range (radio reception) | 87.5...108 MHz |
|-----------------------------------|----------------|

Measurement

| | |
|----------------------|--|
| Extension unit input | extension unit input for separate on/off switching |
|----------------------|--|

Materials

| | |
|------------------------|-----------------|
| Colour of design line | anthracite |
| Material / workmanship | lacquered |
| Material | Mixed materials |
| Surface appearance | velvety |

Installation, mounting

| | |
|-------------------|---|
| Installation mode | single and combination mounting ; screw fastening via supporting plate |
|-------------------|---|

Connection

| | |
|--|--------------------------|
| Conductor cross-section | max. 2.5 mm ² |
| Conductor cross-section (loudspeakers) | max. 1.5 mm ² |
| Type of connection | with screw terminals |

Connection

with 2 loudspeaker connections

Scope of delivery

Component

with one loudspeaker

Equipment

Cylinder

8 station memory, non-volatile ; switch-on with last station

Use

Differentiation characteristic 3 - Sales

with loudspeaker

Identification

Application, usage

Communication technology

Secondary design line(s)

Berker Q.1 ; Berker Q.3 ; Berker Q.7 ; Berker Q.9