



80960326





Cover f. 2gang f. push-button module, clearlenses, Q.x, ant. velvety, lacq.

Technical properties

	_	_	
Λ	rch	itecture	

Fixing mode flush-mounting

Functions

operating concept "independent push-button" function predefined; operating concept for "roller shutter/blind" function predefined; switching of scenes (1..8) possible; brightness value of the status LED for day/nighttime operation preset, change-over for day/nighttime operation possible; integrated temperature sensor with output of the measured values; Colour of status LED uniformly adjustable for complete device; push-button functions: including switching, dimming, roller shutter/blind, timer, priority, operating mode changeover

Easy link functions

Controls and indicators

Button / push-button with programming button and red programming LED

Voltage

Operating voltage over bus 21...32 V DC

Dimensions

Height 58 mm

Power

Power consumption, KNX ≈ 108 mW

Camera

with 2 clear lenses for the RGB status display of the Lens push-button module

Materials

Colour of design line anthracite

RAL colour RAL 7021 - Black grey

Material / workmanship lacquered

Material thermoplastic

Surface appearance velvety

Connection

Type of surface treatment

Bus coupling unit with integral bus coupling unit

Bus connection

bus connection via connecting terminal

Painted

Settings

Supported configuration modes	system
Use	
Differentiation characteristic 2 - Sales	with clear lens
Safety	
Protection index IP	IP20
REACH conform	Yes
RoHS conform	Yes
Halogen free	No
Protection	with dismantling protection
Use conditions	
Operating temperature	-545 °C
Storage/transport temperature	-2070 °C (storage at > 45°C reduces the service life)
Identification	
Application, usage	KNX - operating systems
Product family	product family: push-button
Main design line	KNX - Berker Q.1/Q.3
Secondary design line(s)	KNX, Berker Q.1, Berker Q.3, Berker Q.7, Berker Q.9