



MCB 3P 10kA C-63A 3M

Technical properties

Arc	hite	ctu	re

Number of protected poles	3
Number of poles	3 P
Type of pole	3 P
Curve	С
Functions	
Concurrently switching N-neutral	No
Configuration	
Number of modules	3
Connectivity	
Top connection alignement for modular	
devices	Aligned terminal
Bottom connection alignement for modular devices	Aligned terminal
Main electrical features	
Rated short circuit breaking capacity Icn AC according IEC60898-1	10 kA
Rated operational voltage Ue	230 / 400 V
Type of supply voltage	AC
Frequency	50/60 Hz
Voltage	
Rated insulation voltage	500 V
Rated impulse withstand voltage	4000 V
Electric current	
Rated current	63 A
Rated service breaking capacity Ics AC according IEC 60898-1	7.5 kA
min/maxi threshold value of the AC thermal operation	1.13 / 1.45 ln
Magnetic regulating currrent	5 / 10 In
min/maxi threshold value of the DC magnetic operation	5 / 15 In
min/maxi threshold value of the DC thermal operation	1.13 / 1.45 ln
Breaking capacity on 1 pole for IT 400V NF 60947-2	3 kA
Rated short circuit breaking capacity Icn under 400V AC according IEC60898-1	10 kA

Rated ultimate short-circuit breaking capacity Icu under 415V AC IEC 60947-2 Electric current / temperature Rating current -25°C Rating current -15°C Rating current -10°C Rating current -10°C Rating current 5°C Rating current 5°C Rating current 10°C Rating current 10°C Rating current 15°C Rating current 20°C Rating current 3°C Rating current 15°C Rating current 20°C Rating current 20°C Rating current 20°C Rating current 30°C Rating current 30°C Rating current 40°C Rating current 55°C Rating current 50°C Rating current 50°C Rating current 50°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 1000 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 200 Hz Correction factor of magnetic tripping with 200 Hz	78.9 A 77.6 A 76.2 A 74.9 A 73.5 A 72.1 A 70.7 A 69.2 A 64.6 A 63 A 61.4 A 59.7 A 57.9 A 54.3 A
Rating current -25°C Rating current -15°C Rating current -10°C Rating current -10°C Rating current -5°C Rating current 5°C Rating current 5°C Rating current 5°C Rating current 10°C Rating current 10°C Rating current 15°C Rating current 20°C Rating current 25°C Rating current 30°C Rating current 35°C Rating current 35°C Rating current 40°C Rating current 40°C Rating current 5°C Rating current 50°C Rating current 50°C Rating current 50°C Rating current 60°C Rating current 60°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with Correction factor of magnetic tripping with	77.6 A 76.2 A 74.9 A 73.5 A 72.1 A 70.7 A 69.2 A 67.7 A 66.2 A 64.6 A 59.7 A 57.9 A
Rating current -20°C Rating current -15°C Rating current -10°C Rating current -5°C Rating current 0°C Rating current 5°C Rating current 5°C Rating current 10°C Rating current 15°C Rating current 15°C Rating current 20°C Rating current 20°C Rating current 30°C Rating current 30°C Rating current 35°C Rating current 40°C Rating current 50°C Rating current 50°C Rating current 60°C Rating current 60°C Rating current 60°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	77.6 A 76.2 A 74.9 A 73.5 A 72.1 A 70.7 A 69.2 A 67.7 A 66.2 A 64.6 A 59.7 A 57.9 A
Rating current -15°C Rating current -5°C Rating current 0°C Rating current 0°C Rating current 10°C Rating current 10°C Rating current 15°C Rating current 15°C Rating current 25°C Rating current 25°C Rating current 30°C Rating current 30°C Rating current 35°C Rating current 40°C Rating current 55°C Rating current 55°C Rating current 50°C Rating current 50°C Rating current 50°C Rating current 60°C Rating current 60°C Rating current 60°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	76.2 A 74.9 A 73.5 A 72.1 A 70.7 A 69.2 A 67.7 A 66.2 A 64.6 A 59.7 A 57.9 A 56.1 A
Rating current -10°C Rating current 0°C Rating current 0°C Rating current 10°C Rating current 10°C Rating current 10°C Rating current 15°C Rating current 20°C Rating current 20°C Rating current 30°C Rating current 30°C Rating current 35°C Rating current 40°C Rating current 50°C Rating current 50°C Rating current 50°C Rating current 50°C Rating current 60°C Rating current 60°C Rating current 60°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with Correction factor of magnetic tripping with	74.9 A 73.5 A 72.1 A 70.7 A 69.2 A 67.7 A 66.2 A 61.4 A 59.7 A 57.9 A 56.1 A
Rating current -5°C Rating current 0°C Rating current 5°C Rating current 10°C Rating current 15°C Rating current 15°C Rating current 25°C Rating current 25°C Rating current 30°C Rating current 35°C Rating current 45°C Rating current 45°C Rating current 45°C Rating current 55°C Rating current 55°C Rating current 60°C Rating current 60°C Rating current 60°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with Correction factor of magnetic tripping with	73.5 A 72.1 A 70.7 A 69.2 A 67.7 A 66.2 A 64.6 A 63 A 61.4 A 59.7 A 57.9 A 56.1 A 54.3 A
Rating current 0°C Rating current 10°C Rating current 10°C Rating current 15°C Rating current 20°C Rating current 20°C Rating current 25°C Rating current 35°C Rating current 35°C Rating current 40°C Rating current 40°C Rating current 50°C Rating current 50°C Rating current 50°C Rating current 60°C Rating current 60°C Rating current 60°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with Correction factor of magnetic tripping with Correction factor of magnetic tripping with	72.1 A 70.7 A 69.2 A 67.7 A 66.2 A 64.6 A 63.A 61.4 A 59.7 A 57.9 A 56.1 A
Rating current 5°C Rating current 10°C Rating current 20°C Rating current 20°C Rating current 25°C Rating current 30°C Rating current 35°C Rating current 35°C Rating current 40°C Rating current 45°C Rating current 55°C Rating current 55°C Rating current 50°C Rating current 60°C Rating current 60°C Rating current 60°C Rating current 60°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with Correction factor of magnetic tripping with	70.7 A 69.2 A 67.7 A 66.2 A 64.6 A 63 A 59.7 A 57.9 A 56.1 A
Rating current 10°C Rating current 20°C Rating current 25°C Rating current 25°C Rating current 30°C Rating current 35°C Rating current 40°C Rating current 45°C Rating current 55°C Rating current 55°C Rating current 50°C Rating current 60°C Rating current 60°C Rating current 60°C Rating current 70°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with Correction factor of magnetic tripping with	69.2 A 67.7 A 66.2 A 64.6 A 63 A 61.4 A 59.7 A 57.9 A 56.1 A
Rating current 15°C Rating current 20°C Rating current 30°C Rating current 35°C Rating current 35°C Rating current 40°C Rating current 45°C Rating current 55°C Rating current 55°C Rating current 50°C Rating current 60°C Rating current 65°C Rating current 70°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with Correction factor of magnetic tripping with	67.7 A 66.2 A 64.6 A 63 A 61.4 A 59.7 A 57.9 A 56.1 A
Rating current 20°C Rating current 30°C Rating current 30°C Rating current 35°C Rating current 40°C Rating current 45°C Rating current 50°C Rating current 50°C Rating current 60°C Rating current 60°C Rating current 60°C Rating current 70°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	66.2 A 64.6 A 63 A 61.4 A 59.7 A 57.9 A 56.1 A
Rating current 25°C Rating current 30°C Rating current 35°C Rating current 40°C Rating current 45°C Rating current 50°C Rating current 50°C Rating current 60°C Rating current 60°C Rating current 60°C Rating current 70°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	64.6 A 63 A 61.4 A 59.7 A 57.9 A 56.1 A 54.3 A
Rating current 30°C Rating current 35°C Rating current 40°C Rating current 45°C Rating current 50°C Rating current 55°C Rating current 60°C Rating current 65°C Rating current 70°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	63 A 61.4 A 59.7 A 57.9 A 56.1 A 54.3 A
Rating current 40°C Rating current 45°C Rating current 50°C Rating current 55°C Rating current 55°C Rating current 60°C Rating current 65°C Rating current 65°C Rating current 70°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with Correction factor of magnetic tripping with	61.4 A 59.7 A 57.9 A 56.1 A 54.3 A
Rating current 40°C Rating current 50°C Rating current 50°C Rating current 50°C Rating current 60°C Rating current 65°C Rating current 70°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	59.7 A 57.9 A 56.1 A 54.3 A
Rating current 45°C Rating current 50°C Rating current 60°C Rating current 65°C Rating current 65°C Rating current 70°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	57.9 A 56.1 A 54.3 A
Rating current 50°C Rating current 60°C Rating current 65°C Rating current 65°C Rating current 70°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	56.1 A
Rating current 55°C Rating current 60°C Rating current 65°C Rating current 70°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	54.3 /
Rating current 55°C Rating current 60°C Rating current 65°C Rating current 70°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	
Rating current 60°C Rating current 65°C Rating current 70°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	52.4.7
Rating current 65°C Rating current 70°C Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	JZ.4 F
Current correction factors Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	50.7 <i>A</i>
Correction factor of rating current for 2 devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	48.9 <i>A</i>
devices placed side-by-side Correction factor of rating current for 3 devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	
devices placed side-by-side Correction factor of rating current for 4 and 5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	1
5 devices placed side-by-side Correction factor of rating current for 6 devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	0.95
devices placed side-by-side Correction factor of magnetic tripping with 100 Hz Correction factor of magnetic tripping with	2.0
100 Hz Correction factor of magnetic tripping with	0.85
	1.1
	1.2
Correction factor of magnetic tripping with 400 Hz	1.!
Correction factor of magnetic tripping with 60 Hz	1
Dimensions	
Depth of installed product	70 mm
Height of installed product	83 mm
Width of installed product	
Frequency	52.5 mm
Frequency	52.5 mm

18.1 W
6.24 W
10000
20000
with screw
2,8Nm
NA
metallic
Blconnect
No
No
1 / 35 mm²
1 / 25 mm²
No
EN 60898-1
not concerned
IP20
-2570 °C
3
2000 m
-2580 °C