



# NRN325

# MCB 3P 25kA C-25A 3M

# **Technical properties**

Arc	hi	tec	tu	re
-----	----	-----	----	----

Neutral position	without neutral
Number of protected poles	3
Number of poles	3 P
Type of pole	3 P
Curve	С
Functions	
Concurrently switching N-neutral	No
Configuration	
Number of modules	3
Connectivity	
Top connection alignement for modular devices	Aligned terminal
Bottom connection alignement for modular devices	Aligned terminal
Main electrical features	
Rated short circuit breaking capacity Icn AC according IEC60898-1	10 kA
Rated operational voltage Ue	415 V
Type of supply voltage	AC
Voltage	
Rated insulation voltage	500 V
Max operating voltage	415 V
Rated impulse withstand voltage	6000 V
Electric current	
Rated current	25 A
Rated service breaking capacity Ics AC according IEC 60898-1	7.5 kA
min/maxi threshold value of the AC thermal operation	1.13 / 1.45 ln
Magnetic regulating currrent	5 / 10 In
min/maxi threshold value of the DC magnetic operation	5 / 15 In
min/maxi threshold value of the DC thermal operation	1.13 / 1.45 In
Rating current -10°C according to IEC 60947	35.44 A

Rating current -15°C according to IEC 60947	35.87 A
Rating current -20°C according to IEC 60947	36.3 A
Rating current -25°C according to IEC 60947	36.73 A
Rating current -5°C according to IEC 60947	35.01 A
Rating current 0°C according to IEC 60947	34.58 A
Rating current 10°C according to IEC 60947	33.72 A
Rating current 15°C according to IEC 60947	33.29 A
Rating current 20°C according to IEC 60947	32.86 A
Rating current 25°C according to IEC 60947	32.43 A
Rating current 30°C according to IEC 60947	32 A
Rating current 35°C according to IEC 60947	30.25 A
Rating current 40°C according to IEC 60947	28.5 A
Rating current 45°C according to IEC 60947	26.75 A
Rating current 5°C according to IEC 60947	34.15 A
Rating current 50°C according to IEC 60947	25 A
Rating current 55°C according to IEC 60947	23.25 A
	23.23 A
Rating current 60°C according to IEC 60947	
Rating current 65°C according to IEC 60947	19.75 A
Rating current 70°C according to IEC 60947	18 A
Breaking capacity on 1 pole for IT 400V NF 60947-2	3 kA
Rated short circuit breaking capacity Icn under 230V AC according IEC60898-1	10 kA
Rated short circuit breaking capacity Icn under 400V AC according IEC60898-1	10 kA
Rated ultimate short-circuit breaking capacity Icu under 230V AC IEC 60947-2	50 kA
Rated ultimate short-circuit breaking capacity Icu under 240V AC IEC 60947-2	50 kA
Rated ultimate short-circuit breaking capacity Icu under 400V AC IEC 60947-2	25 kA
Rated ultimate short-circuit breaking capacity Icu under 415V AC IEC 60947-2	25 kA
Rated short circuit breaking capacity Icn under 240V AC according IEC 60898-1	10 kA
Rated short circuit breaking capacity Icn under 415V AC according IEC 60898-1	10 kA
Rated ultimate short-circuit breaking capacity Icu under 220V AC IEC 60947-2	50 kA
Rated ultimate short-circuit breaking capacity Icu under 380V AC IEC 60947-2	25 kA
Current correction factors	
Correction factor of rating current for 2 devices placed side-by-side	1
Correction factor of rating current for 3 devices placed side-by-side	0.95
Correction factor of rating current for 4 and 5 devices placed side-by-side	0.9
Correction factor of rating current for 6 devices placed side-by-side	0.85

Correction factor of magnetic tripping with 200 Hz  Correction factor of magnetic tripping with 400 Hz  Correction factor of magnetic tripping with 60 Hz  Dimensions  Depth of installed product  Height of installed product  Width of installed product  Width of installed product  Frequency  Frequency  Power  Maximum power loss per pole according to the product standard  Total power loss under IN  Power loss per pole at In  Tripping  Time of response when opening  Endurance  Electric endurance in number of cycles  Number of mechanical operations  Installation, mounting  Type of top connection for modular devices  Tightening torque  Type of bottom rail clip for modular devices  Type of bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Bottom removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for massive conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section of the access with	1.1
### ADDRESS OF THE PROPRIES OF	1.2
Dimensions  Depth of installed product  Height of installed product  Width of installed product  Frequency  Frequency  Frequency  Power  Maximum power loss per pole according to the product standard  Total power loss under IN  Power loss per pole at In  Tripping  Time of response when opening  Endurance  Electric endurance in number of cycles  Number of mechanical operations  Installation, mounting  Type of top connection for modular devices  Type of top rail clip for modular devices  Type of Bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	1.5
Depth of installed product  Height of installed product  Width of installed product  Frequency  Frequency  Frequency  Power  Maximum power loss per pole according to the product standard  Total power loss under IN  Power loss per pole at In  Tripping  Time of response when opening  Endurance  Electric endurance in number of cycles  Number of mechanical operations  Installation, mounting  Type of top connection for modular devices  Tightening torque  Type of top rail clip for modular devices  Type of Bottom Connection for modular devices  Type of Bottom Connection for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	1
Height of installed product  Width of installed product  Frequency  Frequency  Power  Maximum power loss per pole according to the product standard  Total power loss under IN  Power loss per pole at In  Tripping  Time of response when opening  Endurance  Electric endurance in number of cycles  Number of mechanical operations  Installation, mounting  Type of top connection for modular devices  Tightening torque  Type of top rail clip for modular devices  Type of Bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Type of Bottom the modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section at output with screws	
Frequency Frequency Frequency Power  Maximum power loss per pole according to the product standard Total power loss under IN Power loss per pole at In  Tripping Time of response when opening  Endurance Electric endurance in number of cycles Number of mechanical operations  Installation, mounting Type of top connection for modular devices Tightening torque Type of top rail clip for modular devices Type of bottom rail clip for modular devices Type of Bottom Connection for modular devices Suitable for flush-mounting  Connection Connection cross-section at output with screw, for flexible conductor Connection cross-section at output with screw, for massive conductor Connection cross-section at output with screw, for massive conductor Connection cross-section for rigid conductor, upstream terminals with screws	70 mm
Frequency  Power  Maximum power loss per pole according to the product standard  Total power loss under IN  Power loss per pole at In  Tripping  Time of response when opening  Endurance  Electric endurance in number of cycles  Number of mechanical operations  Installation, mounting  Type of top connection for modular devices  Tightening torque  Type of top rail clip for modular devices  Type of Bottom Connection for modular devices  Type of Bottom Connection for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section for rigid conductor, upstream terminals with screws	83 mm
Power  Maximum power loss per pole according to the product standard  Total power loss under IN  Power loss per pole at In  Tripping  Time of response when opening  Endurance  Electric endurance in number of cycles  Number of mechanical operations  Installation, mounting  Type of top connection for modular devices  Tightening torque  Type of top rail clip for modular devices  Type of Bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section for rigid conductor, upstream terminals with screws	52.5 mm
Power  Maximum power loss per pole according to the product standard  Total power loss under IN  Power loss per pole at In  Tripping  Time of response when opening  Endurance  Electric endurance in number of cycles  Number of mechanical operations  Installation, mounting  Type of top connection for modular devices  Tightening torque  Type of top rail clip for modular devices  Type of bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	
Maximum power loss per pole according to the product standard  Total power loss under IN  Power loss per pole at In  Tripping  Time of response when opening  Endurance  Electric endurance in number of cycles  Number of mechanical operations  Installation, mounting  Type of top connection for modular devices  Tightening torque  Type of top rail clip for modular devices  Type of bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	50 to 60 Hz
the product standard  Total power loss under IN  Power loss per pole at In  Tripping  Time of response when opening  Endurance  Electric endurance in number of cycles  Number of mechanical operations  Installation, mounting  Type of top connection for modular devices  Tightening torque  Type of top rail clip for modular devices  Type of bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	
Tripping Time of response when opening  Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Type of top connection for modular devices Tightening torque Type of top rail clip for modular devices Type of bottom rail clip for modular devices Type of Bottom Connection for modular devices Top removability for modular devices Bottom removability for modular devices Suitable for flush-mounting  Connection Connection cross-section at output with screw, for flexible conductor Connection cross-section at output with screw, for massive conductor Connection cross-section for rigid conductor, upstream terminals with screws	4.5 W
Tripping Time of response when opening  Endurance Electric endurance in number of cycles Number of mechanical operations Installation, mounting Type of top connection for modular devices Tightening torque Type of top rail clip for modular devices Type of bottom rail clip for modular devices Type of Bottom Connection for modular devices Top removability for modular devices Bottom removability for modular devices Suitable for flush-mounting  Connection Connection cross-section at output with screw, for flexible conductor Connection cross-section at output with screw, for massive conductor Connection cross-section for rigid conductor, upstream terminals with screws	11 W
Endurance  Electric endurance in number of cycles  Number of mechanical operations  Installation, mounting  Type of top connection for modular devices  Tightening torque  Type of top rail clip for modular devices  Type of bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	3.73 W
Electric endurance in number of cycles  Number of mechanical operations  Installation, mounting  Type of top connection for modular devices  Tightening torque  Type of top rail clip for modular devices  Type of bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	
Electric endurance in number of cycles  Number of mechanical operations  Installation, mounting  Type of top connection for modular devices  Tightening torque  Type of top rail clip for modular devices  Type of bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	7 ms
Installation, mounting  Type of top connection for modular devices  Tightening torque  Type of top rail clip for modular devices  Type of bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	
Installation, mounting  Type of top connection for modular devices  Tightening torque  Type of top rail clip for modular devices  Type of bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	4000
Type of top connection for modular devices  Tightening torque  Type of top rail clip for modular devices  Type of bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	20000
Tightening torque  Type of top rail clip for modular devices  Type of bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	
Type of top rail clip for modular devices  Type of bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	with screw
Type of bottom rail clip for modular devices  Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	2,8Nm
Type of Bottom Connection for modular devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	N.A
devices  Top removability for modular devices  Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	plastic
Bottom removability for modular devices  Suitable for flush-mounting  Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	Blconnect
Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	Yes
Connection  Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	Yes
Connection cross-section at output with screw, for flexible conductor  Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	Yes
Connection cross-section at output with screw, for massive conductor  Connection cross-section for rigid conductor, upstream terminals with screws	
screw, for massive conductor  Connection cross-section for rigid  conductor, upstream terminals with screws	1 / 25 mm
conductor, upstream terminals with screws	1 / 35 mm
Connection cross-section of the access with	1 / 35 mm <sup>2</sup>
screws, with flexible conductor	1 / 25 mm <sup>2</sup>
Downstream cage clamp delivery status	opened
Upstream cage clamp delivery status	opened
Equipment	

Yes Can be accessorized

### Standards

Standard text IEC 60947-2

# Safety

REACH conform	No
RoHS conform	Yes
Halogen free	No

# Use conditions

Operating temperature	-2570 °C
Degree of pollution according to IEC 60664 / IEC 60947-2	2
Class of energy limitation I²t	3
Altitude	2000 m
Air humidity protection	for all climates
Storage/transport temperature	-2580 °C

Temperature of calibration

temperatur

50 °C