



TXA227

Output device for 8 shutters 230V~

Technical properties

Architecture

| | |
|-----------------------------------|----------|
| Bus system | KNX |
| Number of blinds/shutters outputs | 8 |
| Fixing mode | Din-Rail |

Functions

| | |
|-----------------------|----|
| Bus module detachable | No |
|-----------------------|----|

Configuration

| | |
|-------------------|---|
| Number of modules | 6 |
|-------------------|---|

Controls and indicators

| | |
|----------------|-----|
| Indicator lamp | yes |
|----------------|-----|

Voltage

| | |
|-----------------------|----------------|
| System supply voltage | 30V DC via bus |
|-----------------------|----------------|

Electric current

| | |
|---------------------------|-----|
| Number of entry circuits | 0 |
| Maximum switching current | 6 A |

Power

| | |
|----------------------------------|--------|
| Contact rating with 230 V in AC1 | 1380 W |
| Total power loss under IN | 4 W |

Materials

| | |
|--------|------------|
| Colour | stone grey |
|--------|------------|

Connection

| | |
|--------------------|---|
| Number of contacts | 8 |
|--------------------|---|

Scope of delivery

| | |
|-------------------------|-----|
| Bus connection included | Yes |
|-------------------------|-----|

Equipment

| | |
|-------------------------------|----|
| Bidirectional radio frequency | No |
|-------------------------------|----|

Safety

| | |
|---------------------|------|
| Protection index IP | IP20 |
|---------------------|------|

Use conditions

| | |
|-----------------------|-----------|
| Operating temperature | 0...45 °C |
|-----------------------|-----------|

