



Rocker, Q.1/Q.3/Q.7, white velvety

Technical characteristics

0	mi	tro	10	- n	a	ind	lica	tors	
L.C	วทา	cro	ıs	an	a	ına	ııca	tors	١

Push-buttons	also for KNX applications: push-button, 1gang, and group push-button, 1gang
Rocker switch/rocker push-button	for rocker push-buttons ; for change- over/intermediate switch
Equipment	
Lighting	for lighting and monitoring circuit
Use	
Differentiation characteristic 2 - Sales	with lens
Identification	
Secondary design line(s)	Berker Q.1 ; Berker Q.3 ; Berker Q.7 ; Berker Q.9
Instructions	
Special note text	The IP44 degree of protection can only be achieved in conjunction with the appropriate neon, incandescent or LED lamp unit, as well as a sealing set for switches/push-buttons.