

503404, 503808

0.4 mA

≈ 100000 h

Light control

Yes

Yes

for lighting and monitoring circuit

for series switch illuminated

black

for change-over/intermediate switch and on/off switch, 2-pole, 10 AX ; for rocker push-buttons and multiple rockers push-buttons, except order no.



168601

**Technical characteristics** 

## **Controls and indicators**

Rocker switch/rocker push-button

.....

Main electrical features

Rated current

Endurance

Service life of the LED

Materials

Colour independent of design lines

## Equipment

Lighting Combination rocker switches/rocker pushbuttons

Use cases

Application

## Safety

REACH conform

Identification

lucitation	
Application, usage	Surface-mounted wet-room installation ; Light control
Main design line	Light control
Secondary design line(s)	Light control ; ACCESSORIES

## Instructions

Special note text	Refer to the overview for the matching flush- mounted inserts. ; these marked articles (see symbol) are only suitable for the water-protected flush-mounted installation IP44 in conjunction with the corresponding seal, frame and contact protection box (imprint "IP44").
Information text	When several LED units are used, the LED current may result in malfunctioning of the relay/pulse relay. Remedy: Carry along a neutral conductor or connect a capacitor 230 V (1 μF per 10 mA LED current) in parallel with the coil.