



185

### Technical characteristics

#### Functions

Function	to limit switch-on currents for problem loads, e.g. energy-saving lamps, electronic ballasts, etc.
----------	--

#### Main electrical features

Frequency	50/60 Hz
-----------	----------

#### Dimensions

Depth	13 mm
Dimensions housing (W x H x D)	≈ 51 x 25 x 13 mm
Height	25 mm
Width	51 mm

#### Materials

Colour independent of design lines	black
------------------------------------	-------

#### Cable

Pre-assembled cable	≈ 80 mm
---------------------	---------

#### Identification

Application, usage	Light control
Main design line	Light control
Secondary design line(s)	Berker Integro Classic, Motion detector, Berker Integro Pure, ACCESSORIES, Berker Integro Flow, Berker Integro Module inserts

#### Instructions

Information text	Due to the small design, suitable for installation in a 40 mm flush-mounted box, e.g. behind universal insert with relay contact, and BLC relay insert. Also suitable for surface-mounted and RMD timer for stairway light.
------------------	---