



VGA socket outlet with screw-in lift terminals, Q.x, alu velvety, lacquered

Technical characteristics

| with straight outlet |
|---|
| S-VGA compatible |
| with 15pole D-subminiature jack (front) |
| |
| max. 160 MHz |
| |
| max. 1280 x 1024 px |
| |
| aluminium |
| RAL 9006 - White aluminium |
| Plastic/metal |
| velvety |
| |
| without spreader claws |
| |
| max. 1.5 mm² |
| with screw-in lift terminals for connection to 15-core VGA cable |
| |
| with supporting ring |
| |
| with screw-in lift terminals |
| |
| Yes |
| Yes |
| No |
| |
| _ , |
| Berker Q.1/Q.3/Q.7/Q.9 |
| |

Instructions

For connecting PCs, notebooks, etc. to display devices such as monitors (including LCD monitors) and projectors.; Observe the instructions of the cable and device manufacturers for maximum VGA cable lengths!; Fränkische: "Multimedia tube" for laying pre-assembled connection cable, Art. no. 294.10.092; Installation recommendation: Kaiser: "Electronic box" for compliance with the permissible bending radii, Art. No. 1068-02 or 9062-74

Information text