



75663785



### S.1/B.3/B.7 Push Button 3-gang, Thermostat/Label, Anthracite/Aluminium

#### Technical characteristics

##### Architecture

Fixing mode flush-mounting

##### Functions

With room temperature controller Yes

Function with valve protection function

Timers with room temperature timer

##### Compatibility

Extension unit extension unit for light scene push-button

##### Controls and indicators

With LED indication Yes

Number of buttons 3

Operation one push-button operation for switching, pushing, shutters and dimming

##### Dimensions

Labelling field length (W x H) 52.3 x 24.9 mm

Height 110.8 mm

Width 55.8 mm

##### Measurement

Value transmitter value transmitter for dimming, position, brightness and temperature values 1 and 2 byte

##### Screen

With display Yes

##### Materials

Colour of labelling 217,217,217

Colour independent of design lines for anthracite and aluminium

Colour other

RAL colour RAL 7021 - Black grey

Material thermoplastic

Material for printing Paper

Type of surface treatment untreated

##### LED control

LED with white operation LED and 6 red status LEDs

##### Connection

**Settings**

Parameterisation	single and two push-button operation parameterisable
------------------	---

**Scope of delivery**

Bus connection included	No
-------------------------	----

**Equipment**

Number of actuation points	8
With anti-theft/dismantling protection	Yes
Type of configuration	Beschriftungsfeld(er) - Folie
Product type:	product type: push-button 3gang
Control	for individual single room temperature control

**Software**

Update	with flash-controller technology
--------	----------------------------------

**Safety**

Protection index IP	IP20
Protection	with dismantling protection
Alarm	alarm telegram after disconnection from bus coupling unit 1 bit or 1 byte

**Use conditions**

Operating temperature	-5...45 °C
Energy efficiency class	IV (2%)

**Identification**

Application, usage	KNX - operating systems
Product family	product family: push-button
Main design line	KNX - Berker S.1/B.3/B.7
Secondary design line(s)	KNX, Berker S.1, Berker B.3, Berker B.7

**Instructions**

Special note text	Use only in combination with frame frame with large cut-out.
-------------------	---