



80142170





Push-button module 2gang, intg temp. sensor, intg bus coupling unit, KNX - K.1

Technical characteristics

Functions	
	operating concept "independent push-button' function predefined; operating concept for "roller shutter/blind" function predefined; switching o' scenes (18) possible; brightness value of the status LED for day/nighttime operation preset
	change-over for day/nighttime operation possible integrated temperature sensor with output of the measured values; Colour of status LED uniformly adjustable for complete device; push-buttor
	functions: including switching, dimming, rolle shutter/blind, timer, priority, operating mode
Easy link functions	changeover
Function	Function for manual interruption of automation functions already triggered
Function Controls and indicators	operating surfaces as buttons (single-surface operation) and rockers (two-surface operation); the brightness of status LEDs are individually adjustable for button/ rocker function; brightness value of the status LEDs for day/nighttime operation adjustable via object or manually; value transmitter for dimming, position, brightness temperature values and 2 byte; integrated temperature sensor with output of the measured values via object parameter defineable lock function; button/rocke functions for switching, dimming, roller shutter/blind value transmitter 1/2 byte, room thermostate extension unit, priority, scene, automatic controduced in the surface of the s
Operation	operating areas configurable as one or two-area operation
Button / push-button	with programming button and red programming LEE
Voltage	
Operating voltage over bus	2132 V DO
Electric current	
Bus current consumption (data transfer)	max. 10 mA
Dimensions	
Insertion depth	31 mn
Height	71 mn
Power	
Power consumption, KNX	≈ 108 mV
Materials	
RAL colour	RAL 7035 - Light grey

LED control	
LED - KNX	with two RGB status LEDs configurable in brightness and colour
Connection	
Bus coupling unit	with integral bus coupling unit
Bus connection	bus connection via connecting terminal
Settings	
Supported configuration modes	system, easy
Equipment	
Product type:	product type: push-button 2gang
Buzzer/siren	with integrated buzzer for acoustic identification of the device within the system
Use	
Differentiation characteristic 1 - Sales	with RGB LED
Differentiation characteristic 2 - Sales	with integrated temperature sensor
Differentiation characteristic 3 - Sales	with integral bus coupling unit
Safety	
REACH conform	No
RoHS conform	Yes
Halogen free	No
Protection	with dismantling protection
Use conditions	
Operating temperature	-545 °C
Storage/transport temperature	-2070 °C (storage at > 45°C reduces the service life)
Temperature	integrated temperature sensor with output of the measured values via object
Identification	
Application, usage	KNX - operating systems
Product family	product family: push-button
Main design line	KNX

KNX ; Berker Q.1 ; Berker Q.3 ; Berker Q.7 ; Berker Q.9 ; Berker K.1 ; Berker K.5

Secondary design line(s)