




80163776



Push-button 3gang, lab. field, + RGB LED, internal temp. sensor, KNX - K.1, ant.

Technical characteristics

Fixing mode flush-mounting

Functions

Easy link functions

Function

With room temperature controller Yes

operating concept "independent push-button" function predefined, operating concept for "roller shutter/blind" function predefined, switching of scenes (1..8) possible, Orientation LED can be controlled via object, brightness value of the status LED for day/nighttime operation preset, status LED for day/nighttime operation can be controlled via object, integrated temperature sensor with output of the measured values, Colour of status LED uniformly adjustable for complete device, push-button functions: including switching, dimming, roller shutter/blind, timer, priority, temperature setpoint adjustment, operating mode changeover

Function for manual interruption of automatic functions already triggered

operating surfaces as buttons (single-surface operation) and rockers (two-surface operation), the brightness of status LEDs are individually adjustable for button/ rocker function, brightness value of the status LEDs for day/nighttime operation adjustable via object or manually, value transmitter for dimming, position, brightness temperature values ${\bf 1}$ and 2 byte, button/rocker functions for switching, dimming, roller shutter/blind, value transmitter 1/2 byte, room thermostat extension unit, priority, scene, automatic control deactivation, integrated temperature sensor with output of the measured values via object, button functions for switching, dimming, roller shutter/blind, timer, value transmitter 1/2 byte, room thermostat extension unit, priority, scene, 2-channel mode, step switch, automatic control deactivation, rocker functions for switching, dimming, roller shutter/blind, value transmitter 1/2 byte, room thermostat extension unit, priority, scene, 2-channel mode, automatic control deactivation, 3-step switch, function for incremental selection of up to 7 stored values, parameter defineable lock function, Status LED configurable in its colour per button

Function

Controls and indicators

With LED indication	Yes
Number of buttons	3
Operation	operating areas configurable as one or two-area operation

Electric current

Bus current consumption (data transfer) max. 20 mA

Dimensions

Labelling field length (W x H)	66.8 x 15.7 mm
Height	15.7 mm
Width	66 mm
Power	
Power consumption, KNX	≈ 150 mV
Measurement	
Value transmitter	value transmitter for dimming, position, brightness and temperature values 1 and 2 byte
Screen	
With display	N
Materials	
Material	thermoplastic
Material for printing	Pape
Material family	Plastic
LED control	
LED	with white operating LED, with 2 RGB status LED: per rocke
Connection	
Bus coupling unit	for bus coupling unit flush-mounted
Settings	
Supported configuration modes	system, easy
Parameterisation	single and two push-button operatior parameterisable
Scope of delivery	
Bus connection included	No
Equipment	
Number of actuation points	(
With anti-theft/dismantling protection	Ye
Product type:	product type: push-button 3gan
Use	
Differentiation characteristic 1 - Sales	with labelling field:
Differentiation characteristic 2 - Sales	and RGB LED
Differentiation characteristic 3 - Sales	with integrated temperature senso
Safety	
Protection index IP	IP20
REACH conform	Ye
RoHS conform	Ye
Halogen free	No
Protection	with dismantling protection
Alarm	alarm telegram after disconnection from but coupling unit 1 bit or 1 byte
	coupling unit I bit of I byte

Use conditions	
Operating temperature	-545 °C
Storage/transport temperature	-2070 °C (storage at > 45°C reduces the service life)
Temperature	integrated temperature sensor with output of the measured values via object
Identification	
Application, usage	KNX - operating systems
Product family	product family: push-button
Secondary design line(s)	KNX, Berker K.1, Berker K.5
Instructions	
Special note text	Use only in conjunction with bus coupling unit 8004 00 01!